

# SAA3006

## Infrared Transmitter

### Product Specification

## Linear Products

### DESCRIPTION

The SAA3006 is intended as a general purpose (RC-5) infrared remote control system for use where only low supply voltages are available. The device can generate 2048 different commands and utilizes a keyboard with a single-pole switch per key. The commands are arranged so that 32 systems can be addressed, each system containing 64 different commands.

The circuit response to legal (one key pressed at a time) and illegal (more than one key pressed at a time) keyboard operation is specified later in this publication (see KEY ACTIVITIES).

## FEATURES

- Low supply voltage requirements
- Very low current consumption
- For infrared transmission link
- Transmitter for  $32 \times 64$  commands
- One transmitter controls 32 systems
- Transmission biphase technique
- Short transmission times; speed-up of system reaction time
- Single-pin oscillator input
- Input protection
- Test mode facility

## APPLICATIONS

- Audio
- TV

## ORDERING INFORMATION

DESCRIPTION	TEMPERATURE RANGE	ORDER CODE
28-Pin Plastic DIP (SOT-117)	-25°C to +85°C	SAA3006PN


### ABSOLUTE MAXIMUM RATINGS

SYMBOL	PARAMETER	RATING	UNIT
V <sub>DD</sub>	Supply voltage range with respect to V <sub>SS</sub>	−0.5 to +8.5	V
V <sub>I</sub>	Input voltage range	−0.5 to (V <sub>DD</sub> + 0.5)	V <sup>1</sup>
+I <sub>I</sub>	Input current	10	mA
V <sub>O</sub>	Output voltage range	−0.5 to (V <sub>DD</sub> + 0.5)	V <sup>1</sup>
+I <sub>O</sub>	Output current	10	mA
P <sub>O</sub>	Power dissipation output OSC	50	mW
P <sub>O</sub>	Power dissipation per output (all other outputs)	100	mW
P <sub>TOT</sub>	Total power dissipation per package	200	mW
T <sub>A</sub>	Operating ambient temperature range	−25 to +85	°C
T <sub>STG</sub>	Storage temperature range	−65 to +150	°C

**NOTE:**

1.  $V_{DD} + 0.5V$  not to exceed 9V.


## PIN CONFIGURATION



## Infrared Transmitter

SAA3006

## BLOCK DIAGRAM



## Infrared Transmitter

SAA3006

**DC ELECTRICAL CHARACTERISTICS**  $V_{SS} = 0V$ ;  $T = -25$  to  $85^{\circ}C$ , unless otherwise specified.


SYMBOL	PARAMETER	$V_{DD}$ (V)	LIMITS			UNIT
			Min	Typ	Max	
$V_{DD}$	Supply voltage		2		7	V
	Supply current at $I_O = 0mA$ for all outputs; X0 to X7 and Z3 at $V_{DD}$ ; all other inputs at $V_{DD}$ or $V_{SS}$ ; excluding leakage current from open-drain N-channel outputs					
$I_{DD}$	$T_A = 25^{\circ}C$	7			10	$\mu A$
<b>Inputs</b> Keyboard inputs X and Z with P-channel pull-up transistors						
$-I_i$	Input current (each input) at $V_i = 0V$ ; TP = SSM = LOW	2 to 7	10		600	$\mu A$
$V_{IH}$	Input voltage HIGH	2 to 7	$0.7 \times V_{DD}$		$V_{DD}$	V
$V_{IL}$	Input voltage LOW	2 to 7	0		$0.3 \times V_{DD}$	V
$I_{IR}$ $-I_{IR}$	Input leakage current at $T_A = 25^{\circ}C$ ; TP = HIGH; $V_i = 7V$ $V_i = 0V$				1 1	$\mu A$ $\mu A$
<b>SSM, TP1 and TP2</b>						
$V_{IH}$	Input voltage HIGH	2 to 7	$0.7 \times V_{DD}$		$V_{DD}$	V
$V_{IL}$	Input voltage LOW	2 to 7	0		$0.3 \times V_{DD}$	V
$I_{IR}$ $-I_{IR}$	Input leakage current at $T_A = 25^{\circ}C$ ; $V_i = 7V$ $V_i = 0V$				1 1	$\mu A$ $\mu A$
<b>OSC</b>						
$-I_i$	Input leakage current at $T_A = 25^{\circ}C$ ; $V_i = 0V$ ; TP1 = HIGH; Z2 = Z3 = LOW	2 to 7			2	$\mu A$
<b>Outputs DATA and MDATA</b>						
$V_{OH}$	Output voltage HIGH at $-I_{OH} = 0.4mA$	2 to 7	$V_{DD} - 0.3$			V
$V_{OL}$	Output voltage LOW at $I_{OL} = 0.6mA$	2 to 7			0.3	V
$I_{OR}$ $-I_{OR}$	Output leakage current at: $V_O = 7V$ $V_O = 0V$				10 20	$\mu A$ $\mu A$
$I_{OR}$ $-I_{OR}$	$T_A = 25^{\circ}C$ ; $V_O = 7V$ $V_O = 0V$				1 2	$\mu A$ $\mu A$
<b>DR0 to DR7, TP2</b>						
$V_{OL}$	Output voltage LOW at $I_{OL} = 0.3mA$	2 to 7			0.3	V
$I_{OR}$ $I_{OR}$	Output leakage current at $V_O = 7V$ at $V_O = 7V$ ; $T_A = 25^{\circ}C$	7			10 1	$\mu A$ $\mu A$

Infrared Transmitter

SAA3006

DC ELECTRICAL CHARACTERISTICS (Continued)  $V_{SS} = 0V$ ;  $T = -25$  to  $85^{\circ}C$ , unless otherwise specified.

SYMBOL	PARAMETER	V <sub>DD</sub> (V)	LIMITS			UNIT
			Min	Typ	Max	
OSC						
I <sub>osc</sub>	Oscillator current at OSC = V <sub>DD</sub>	7	4.5		30	μA
Oscillator						
f <sub>osc</sub>	Maximum oscillator frequency at C <sub>L</sub> = 40pF (Figures 4 and 5)	2			450	kHz
f <sub>osc</sub>	Free-running oscillator frequency at T <sub>A</sub> = 25°C	2	10		120	kHz



## Infrared Transmitter

SAA3006

## FUNCTIONAL DESCRIPTION

Combined System Mode  
(SSM = LOW)

The X and Z lines are active-HIGH in the quiescent state. Legal key operation either in the X-DR or Z-DR matrix starts the debounce cycle. When the contact is made for two bit times without interruption, the oscillator enable signal is latched and the key may be released. Interruption within the two bit times resets the internal action. At the end of the debounce time, the DR outputs are switched off and two scan cycles are started, switching on the DR-outputs one by one. When a Z or X input senses a LOW level, a latch enable signal is fed to the system address or command latches, depending on whether sensing was found in the Z or X input matrix. After latching a system address number, the device will generate the last command (i.e., all command bits '1') in the chosen system as long as the key is pressed. Latching of a command number causes the device to generate this command together with the system address number stored in the system address latch. Releasing the key will reset the internal action if no data is transmitted at that time. Once the transmission is started, the signal will be finished completely.

Single System Mode  
(SSM = HIGH)

The X lines are active-HIGH in the quiescent state; the pull-up transistors of the Z lines are switched off and the inputs are disabled. Only legal key operation in the X-DR matrix starts the debounce cycle. When the contact is made for two bit times without interruption, the oscillator enable signal is latched and the key may be released. Interruption within the two bit times resets the internal action. At the end of the debounce time, the pull-up transistors in the X lines are switched off. Those in the Z lines are switched on during the first scan cycle. The wired connection in the Z matrix is then translated into a system address number and stored in the system ad-

dress latch. At the end of the first scan cycle the pull-up transistors in the Z lines are switched off and the inputs are disabled again, while the transistors in the X lines are switched on. The second scan cycle produces the command number which, after latching, is transmitted together with the system address number.

## Inputs

The command inputs X0 to X7 carry a logical '1' in the quiescent state by means of an internal pull-up transistor. When SSM is LOW, the system inputs Z0 to Z3 also carry a logical '1' in the quiescent state by means of an internal pull-up transistor.

When SSM is HIGH, the transistors are switched off and no current flows via the wired connection in the Z-DR matrix.

## Oscillator

The oscillator is formed by a ceramic resonator (catalog number 2422 540 98021 or equivalent) feeding the single-pin input OSC. Direct connection is made for supply voltages in the range 2 to 5.25V but it is necessary to fit a 10k $\Omega$  resistor in series with the resonator when using supply voltages in the range 2.6 to 7V.

## Key Release Detection

An extra control bit is added which will be complemented after key release. In this way the decoder gets an indication that shows if the next code is to be considered as a new command. This is very important for multi-digit entry (e.g., by channel numbers or Teletext/Viewdata pages). The control bit will only be complemented after finishing at least one code transmission. The scan cycles are repeated before every code transmission, so that, even by 'takeover' of key operation during the code transmission, the correct system and command numbers are generated.

## Outputs

The output DATA carries the generated information according to the format given in Figure 2 and Tables 2 and 3. The code is

transmitted in biphase; definitions of logical '1' and '0' are given in Figure 3.

The code consists of four parts:

- Start part formed by 2 bits (two times a logical '1')
- Control part formed by 1 bit
- System part formed by 5 bits
- Command part formed by 6 bits.

The output MDATA carries the same information as output DATA but is modulated on a carrier frequency of  $\frac{1}{12}$  the oscillator frequency, so that each bit is presented as a burst of 32 pulses. To reduce power consumption, the carrier frequency has a 25% duty cycle.

In the quiescent state, both outputs are non-conducting (3-state outputs). The scan drivers DR0 to DR7 are of the open-drain N-channel type and are conducting in the quiescent state of the circuit. After a legal key operation all the driver outputs go into the high ohmic state; a scanning procedure is then started so that the outputs are switched into the conducting state one after the other.

## Reset Action

The circuit will be reset immediately when a key release occurs during:

- Debounce time
- Between two codes.

When a key release occurs during scanning of the matrix, a reset action will be accomplished if:

- The key is released while one of the driver outputs is in the low-ohmic '0' state
- The key is released before detection of that key
- There is no wired connection in the Z-DR matrix while SSM is HIGH.

## Test Pin

The test pins TP1 and TP2 are used for testing in conjunction with inputs Z2 and Z3 as shown in Table 1.

Table 1. Test Functions

TP1	TP2	Z2	Z3	FUNCTION
LOW	LOW	Matrix input	Matrix input	Normal
LOW	HIGH	Matrix input	Matrix input	Scan + output frequency 6 times faster than normal
HIGH	Output $f_{osc}^6$	LOW	LOW	Reset
HIGH	Output $f_{osc}^6$	HIGH	HIGH	Output frequency $3 \times 2^7$ faster than normal

## Infrared Transmitter

SAA3006

## KEY ACTIVITIES

Every connection of one X input and one DR output is recognized as a legal keyboard operation and causes the device to generate the corresponding code.

Activating more than one X input at a time is an illegal keyboard operation and no circuit action is taken (oscillator does not start).

When SSM is LOW, every connection of one Z input and one DR output is recognized as a legal keyboard operation and causes the device to generate the corresponding code.

Activating two or more Z inputs, or Z inputs and X inputs, at one time is an illegal keyboard operation and no circuit action is taken.

When SSM is HIGH, a wired connection must be made between a Z input and a DR output. If no connection is made, the code is not generated.

When one X or Z input is connected to more than one DR output, the last scan signal is considered legal.

The maximum allowable value of the contact series resistance of the keyboard switches is  $7k\Omega$ .




Figure 2. DATA Output Format (RC-5)




Figure 3. Biphase Transmission Code

## Infrared Transmitter

SAA3006

Table 2. Command Matrix X-DR

CODE NO	X-LINES X							DR-LINES DR							COMMAND BITS C							
	0	1	2	3	4	5	6	7	0	1	2	3	4	5	6	7	5	4	3	2	1	0
0	•								•								0	0	0	0	0	0
1	•									•							0	0	0	0	0	1
2	•										•						0	0	0	0	1	0
3	•											•					0	0	0	0	1	1
4	•												•				0	0	0	1	0	0
5	•													•			0	0	0	1	0	1
6	•														•		0	0	0	1	1	0
7	•															•	0	0	0	1	1	1
8		•							•								0	0	1	0	0	0
9		•								•							0	0	1	0	0	1
10		•									•						0	0	1	0	1	0
11		•										•					0	0	1	0	1	1
12		•											•				0	0	1	1	0	0
13		•												•			0	0	1	1	0	1
14		•													•		0	0	1	1	1	0
15		•														•	0	0	1	1	1	1
16			•						•								0	1	0	0	0	0
17			•							•							0	1	0	0	0	1
18			•								•						0	1	0	0	1	0
19			•									•					0	1	0	0	1	1
20			•										•				0	1	0	1	0	0
21			•											•			0	1	0	1	0	1
22			•												•		0	1	0	1	1	0
23			•													•	0	1	0	1	1	1
24				•					•								0	1	1	0	0	0
25				•						•							0	1	1	0	0	1
26				•							•						0	1	1	0	1	0
27				•								•					0	1	1	0	1	1
28				•									•				0	1	1	1	0	0
29				•										•			0	1	1	1	0	1
30				•											•		0	1	1	1	1	0
31				•												•	0	1	1	1	1	1

## Infrared Transmitter

SAA3006

Table 2. Command Matrix X-DR (Continued)

CODE NO	X-LINES X								DR-LINES DR								COMMAND BITS C					
	0	1	2	3	4	5	6	7	0	1	2	3	4	5	6	7	5	4	3	2	1	0
32					•				•								1	0	0	0	0	0
33					•					•							1	0	0	0	0	1
34					•						•						1	0	0	0	1	0
35					•							•					1	0	0	0	1	1
36					•								•				1	0	0	1	0	0
37					•									•			1	0	0	1	0	1
38					•										•		1	0	0	1	1	0
39					•											•	1	0	0	1	1	1
40						•			•								1	0	1	0	0	0
41						•				•							1	0	1	0	0	1
42						•					•						1	0	1	0	1	0
43						•						•					1	0	1	0	1	1
44						•							•				1	0	1	1	0	0
45						•								•			1	0	1	1	0	1
46						•									•		1	0	1	1	1	0
47						•										•	1	0	1	1	1	1
48							•		•								1	1	0	0	0	0
49							•			•							1	1	0	0	0	1
50							•				•						1	1	0	0	1	0
51							•					•					1	1	0	0	1	1
52							•						•				1	1	0	1	0	0
53							•							•			1	1	0	1	0	1
54							•								•		1	1	0	1	1	0
55							•									•	1	1	0	1	1	1
56								•	•								1	1	1	0	0	0
57								•		•							1	1	1	0	0	1
58								•			•						1	1	1	0	1	0
59								•				•					1	1	1	0	1	1
60								•					•				1	1	1	1	0	0
61								•						•			1	1	1	1	0	1
62								•							•		1	1	1	1	1	0
63								•								•	1	1	1	1	1	1




Infrared Transmitter

SAA3006

Table 3. System Matrix Z-DR

SYSTEM NO	Z-LINES Z				DR-LINES DR								SYSTEM BITS S				
	0	1	2	3	0	1	2	3	4	5	6	7	4	3	2	1	0
0	•				•								0	0	0	0	0
1	•					•							0	0	0	0	1
2	•						•						0	0	0	1	0
3	•							•					0	0	0	1	1
4	•								•				0	0	1	0	0
5	•									•			0	0	1	0	1
6	•										•		0	0	1	1	0
7	•											•	0	0	1	1	1
8		•			•								0	1	0	0	0
9		•				•							0	1	0	0	1
10		•					•						0	1	0	1	0
11		•						•					0	1	0	1	1
12		•							•				0	1	1	0	0
13		•								•			0	1	1	0	1
14		•									•		0	1	1	1	0
15		•										•	0	1	1	1	1
16			•		•								1	0	0	0	0
17			•			•							1	0	0	0	1
18			•				•						1	0	0	1	0
19			•					•					1	0	0	1	1
20			•						•				1	0	1	0	0
21			•							•			1	0	1	0	1
22			•								•		1	0	1	1	0
23			•									•	1	0	1	1	1
24				•	•								1	1	0	0	0
25				•		•							1	1	0	0	1
26					•		•						1	1	0	1	0
27						•		•					1	1	0	1	1
28							•		•				1	1	1	0	0
29								•		•			1	1	1	0	1
30									•		•		1	1	1	1	0
31										•		•	1	1	1	1	1



HANDLING

Inputs and outputs are protected against electrostatic charge in normal handling. However, to be totally safe, it is desirable to take normal precautions appropriate to handling MOS devices.

