

FAST RECOVERY RECTIFIER DIODES

- FAST RECOVERY TIME
- LOW FORWARD RECOVERY TIME

APPLICATIONS

- DC AND AC MOTOR CONTROL
- SWITCHMODE POWER SUPPLY
- HIGH FREQUENCY CHOPPERS
- HIGH FREQUENCY RECTIFIERS



DO 4
(Metal)

ABSOLUTE RATINGS (limiting values)

Symbol	Parameter	Value		Unit
$I_{F_{RM}}$	Repetitive Peak Forward Current	$t_p \leq 20\mu s$	130	A
$I_F (AV)$	Average Forward Current	$T_C = 100^\circ C$	6	A
$I_{F_{SM}}$	Surge non Repetitive Forward Current	$t_p = 10ms$ Sinusoidal	150	A
P_{tot}	Power Dissipation	$T_C = 100^\circ C$	20	W
T_{stg} T_J	Storage and Junction Temperature Range	– 65 to 150		°C

Symbol	Parameter	1N					Unit
		3879	3880	3881	3882	3883	
V_{RRM}	Repetitive Peak Reverse Voltage	50	100	200	300	400	V

THERMAL RESISTANCE

Symbol	Parameter	Value		Unit
$R_{th} (j-c)$	Junction-case	2.5		°C/W

ELECTRICAL CHARACTERISTICS**STATIC CHARACTERISTICS**

Symbol	Test Conditions		Min.	Typ.	Max.	Unit
I_R	$T_j = 25^\circ C$	$V_R = V_{RRM}$			15	μA
	$T_j = 100^\circ C$				1	mA
V_F	$T_j = 25^\circ C$	$I_F = 6A$			1.4	V

RECOVERY CHARACTERISTICS

Symbol	Test Conditions			Min.	Typ.	Max.	Unit
t_{rr}	$T_j = 25^\circ C$	$I_F = 1A$	$dI_F/dt = -15A/\mu s$			200	ns
Q_{rr}	$T_j = 25^\circ C$	$I_F = 1A$	$dI_F/dt = -15A/\mu s$			0.2	μC
I_{RM}	$T_j = 25^\circ C$	$I_F = 1A$	$dI_F/dt = -15A/\mu s$			2	A

To evaluate the conduction losses use the following equations :

$$V_F = 1.2 + 0.02 I_F \quad P = 1.2 \times I_F(AV) + 0.02 I_F^2(RMS).$$