DS7820A/DS8820A Dual Line Receiver

General Description


The DS7820A and the DS8820A are improved performance digital line receivers with two completely independent units fabricated on a single silicon chip. Intended for use with digital systems connected by twisted pair lines, they have a differential input designed to reject large common mode signals while responding to small differential signals. The output is directly compatible with TTL or LS integrated circuits. The response time can be controlled with an external capacitor to reject input noise spikes. The output state is a logic "1" for both inputs open. Termination resistors for the twisted pair line are also included in the circuit. Both the DS7820A and the DS8820A are specified, worst case, over

their full operating temperature range (-55° C to $+125^{\circ}$ C and 0°C to 70°C respectively), over the entire input voltage range, for $\pm 10\%$ supply voltage variations.

Features

- Operation from a single +5V logic supply
- Input voltage range of ±15V
- Strobe low forces output to "1" state
- High input resistance
- Fanout of ten with TTL integrated circuits
- Outputs can be wire OR'ed
- Series 54/74 compatible

Connection Diagram



TL/F/5797-2

Order Number DS7820AJ or DS8820AN See NS Package Number J14A or N14A

For Complete Military 883 Specifications, See RETS Data Sheet.
Order Number DS7820AJ/883 or DS7820AW/883
See NS Package Number J14A or W14B

Absolute Maximum Ratings (Note 1) If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications. Supply Voltage 8.0V Common-Mode Voltage ± 20V Differential Input Voltage ± 20V Strobe Voltage 8.0V

Output Sink Current 50 mA Storage Temperature Range -65°C to 150°C

Maximum Power Dissipation* at 25°C

Cavity Package 1308 mW
Molded Package 1207 mW
Lead Temperature (Soldering, 4 sec.) 260°C

*Derate cavity package 8.7 mW/°C above 25°C; derate molded package 9.7 mW/°C above 25°C.

Operating Cond	ditions		
-	Min	Max	Units
Supply Voltage (V _{CC})			50
DS7820A	4.5	5.5	٧
DS8820A	4.75	5.25	٧
Temperature (T _A)			
DS7820A	-55	+ 125	°C
DS8820A	0	+70	°C

Electrical Characteristics (Notes 2, 3, and 4)

Symbol	Parameter	Conditions			Min	Тур	Max	Units
V _{TH}	Differential Threshold Voltage	$I_{OUT} = -400 \mu A,$ $V_{OUT} \ge 2.5 V$	-3V ≤ V _{CM} ≤	+ 3V		0.06	0.5	٧
			-15V ≤ V _{CM} ≤	≤ +15V		0.06	1.0	٧
		$I_{OUT} = +16 \text{ mA},$	-3V ≤ V _{CM} ≤	+3V		-0.08	-0.5	٧
		V _{OUT} ≤ 0.4V	-15V ≤ V _{CM} ≤	≤ +15V		-0.08	-1.0	٧
R _I -	Inverting Input Resistance	$-15V \le V_{\text{CM}} \le +1$	5V		3.6	5		kΩ
Ri ⁺ ,	Non-Inverting Input Resistance	$-15V \le V_{CM} \le +15V$		1.8	2.5		kΩ	
RT	Line Termination Resistance	T _A = 25°C		120	170	250	Ω	
h_	Inverting Input Current	V _{CM} = 15V			3.0	4.2	mA	
	V _{CM} = 0V			0	-0.5	mA		
		$V_{CM} = -15V$			-3.0	-4.2	mA	
II + Non-Inverting Input Current	V _{CM} = 15V			5.0	7.0	mA		
	V _{CM} = 0V			-1.0	-1.6	mA		
		V _{CM} = -15V			-7.0	-9.8	mA	
١ ٠٠	Power Supply Current One Side Only	I _{OUT} = Logical "0"	$V_{DIFF} = -1V \frac{V_{CM} = 15V}{V_{CM} = -15V}$		3.9	6.0	mA	
				$V_{CM} = -15V$		9.2	14.0	mA
			V _{DIFF} = -0.5\	/, V _{CM} = 0V		6.5	10.2	mA
V _{OH}	Logical "1" Output Voltage	$I_{OUT} = -400 \mu\text{A}, V_{DIFF} = 1V$		2.5	4.0	5.5	٧	
V _{OL}	Logical "0" Output Voltage	$I_{OUT} = +16 \text{ mA}, V_{DIFF} = -1V$		0	0.22	0.4	٧	
V _{SH}	Logical "1" Strobe Input Voltage	$I_{OUT} = +16 \text{ mA}, V_{OUT} \le 0.4 \text{V}, V_{DIFF} = -3 \text{V}$		2.1			٧	
V _{SL}	Logical "0" Strobe Input Voltage	$I_{OUT} = -400 \mu A$, $V_{OUT} \ge 2.5 V$, $V_{DIFF} = -3 V$					0.9	٧
I _{SH}	Logical "1" Strobe Input Current	V _{STROBE} = 5.5V, V _{DIFF} = 3V			0.01	5.0	μΑ	
I _{SL}	Logical "0" Strobe Input Current	V _{STROBE} = 0.4V, V _{DIFF} = -3V				-1.0	-1.4	mA
Isc	Output Short Circuit Current	V _O = 0V, V _{CC} = 5.5V, V _{STROBE} = 0V			-2.8	-4.5	-6.7	mA

Note 1: "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. Except for "Operating Temperature Range" they are not meant to imply that the devices should be operated at these limits. The table of "Electrical Characteristics" provides conditions for actual device operation.

Note 2: These specifications apply for $4.5 \text{V} \le \text{V}_{\text{CC}} \le 5.5 \text{V}, -15 \text{V} \le \text{V}_{\text{CM}} \le 15 \text{V} \text{ and } -55^{\circ}\text{C} \le T_{\text{A}} \le +125^{\circ}\text{C}$ for the DS7820A or $4.75 \text{V} \le \text{V}_{\text{CC}} \le 5.25 \text{V}, 0^{\circ}\text{C} \le T_{\text{A}} \le +70^{\circ}\text{C}$ for the DS8820A unless otherwise specified. Typical values given are for $\text{V}_{\text{CC}} = 5.0 \text{V}, T_{\text{A}} = 25^{\circ}\text{C}$ and $\text{V}_{\text{CM}} = 0 \text{V}$ unless stated differently.


Note 3: All currents into device pins shown as positive, out of device pins as negative, all voltages referenced to ground unless otherwise noted. All values shown as max or min on absolute value basis.

Note 4: Only one output at a time should be shorted.


Switching Characteristics TA = 25°C	$C. V_{CC} = 5V.$ unless otherwise noted
-------------------------------------	------------------------------------------

Symbol	Parameter	Conditions	Min	Тур	Max	Units
t _{pd0}	Propagation Delay, Differential Input to "0" Output	$R_{\rm L}=400~\Omega, C_{\rm L}=15~ m pF, see~\it Figure~1$		30	45	ns
t _{pd1}	Propagation Delay, Differential Input to "1" Output			27	40	ns
t _{pd0}	Propagation Delay, Strobe Input to "0" Output			16	25	ns
^t pd1	Propagation Delay, Strobe Input to "1" Output			18	30	ns

AC Test Circuit and Waveforms



TL/F/5797-7




TL/F/5797-8


- A = Differential Input to "0" Output
- B = Differential Input to "1" Output
- C = Strobe Input to "0" Output
- D = Strobe input to "1" Output

FIGURE 1

Typical Performance Characteristics (Note 3)



Schematic Diagram




TL/F/5797-1

TL/F/5797-3

Typical Applications

Differential Line Driver and Receiver



Single Ended (EIA-RS232C) Receiver with Hysteresis

