



DS90CF581/DS90CF582

LVDS 24-Bit Color Flat Panel Display (FPD) Link


General Description

The DS90CF581 transmitter converts 28 bits of CMOS/TTL data into four LVDS (Low Voltage Differential Signaling) data streams. A phase-locked transmit clock is transmitted in parallel with the data streams over a fifth LVDS link. Every cycle of the transmit clock 28 bits of input data are sampled and transmitted. The DS90CF582 receiver converts the LVDS data streams back into 28 bits of CMOS/TTL data. At a transmit clock frequency of 40 MHz, 24 bits of RGB data and 4 bits of LCD timing and control data (FPLINE, FPFRAME, DRDY, CNTL) are transmitted at a rate of 280 Mbps per LVDS data channel. Using a 40 MHz clock, the data throughput is 140 Megabytes per second. The chipset is an ideal means to solve EMI and cable size problems associated with wide, high speed TTL interfaces.

Features

- Up to 140 Megabyte/sec Bandwidth
- Narrow bus reduces cable size
- 345 mV swing LVDS devices for low EMI
- Low power CMOS design
- Power-down mode
- PLL requires no external components
- Low profile 56-lead TSSOP package
- Falling edge data strobe
- Compatible with TIA/EIA-644 LVDS standard

Block Diagrams




TL/F/12486-1

Order Number **DS90CF581MTD**
See NS Package Number MTD56


Order Number **DS90CF582MTD**
See NS Package Number MTD56

Application




TL/F/12486-2

Connection Diagrams



TL/F/12486-3



TL/F/12486-4

Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

Supply Voltage (V_{CC})	−0.3 to +6V
CMOS/TTL Input Voltage	−0.3 to ($V_{CC} + 0.3V$)
CMOS/TTL Output Voltage	−0.3 to ($V_{CC} + 0.3V$)
LVDS Receiver Input Voltage	−0.3 to ($V_{CC} + 0.3V$)
LVDS Driver Output Voltage	−0.3 to ($V_{CC} + 0.3V$)
LVDS Output Short Circuit Duration	continuous
Junction Temperature	+150°C
Storage Temperature Range	−65°C to +150°C
Lead Temperature (Soldering, 4 sec.)	+260°C

Maximum Package Power Dissipation @ +25°C

MTD56 (TSSOP) Package: DS90CF581 1.63W

DS90CF582 1.61W

Derate Package: DS90CF581 12.5 mW/°C above +25°C

DS90CF582 12.4 mW/°C above +25°C

This device does not meet 2000V ESD rating. (Note 4)

Recommended Operating Conditions

	Min	Nom	Max	Units
Supply Voltage (V_{CC})	4.5	5.0	5.5	V
Operating Free				
Air Temperature (T_A)	−10	+25	+70	°C
Receiver Input Range	0		2.4	V

Electrical Characteristics

Over recommended operating supply and temperature ranges unless otherwise specified

Symbol	Parameter	Conditions	Min	Typ	Max	Units
CMOS/TTL DC SPECIFICATIONS						
V_{IH}	High Level Input Voltage		2.0		V_{CC}	V
V_{IL}	Low Level Input Voltage		GND		0.8	V
V_{OH}	High Level Output Voltage	$I_{OH} = -0.4$ mA	3.8	4.9		V
V_{OL}	Low Level Output Voltage	$I_{OL} = 2$ mA		0.1	0.3	V
V_{CL}	Input Clamp Voltage	$I_{CL} = -18$ mA		−0.79	−1.5	V
I_{IN}	Input Current	$V_{IN} = V_{CC}, GND, 2.5V$ or 0.4V		±5.1	±10	μA
I_{OS}	Output Short Circuit Current	$V_{OUT} = 0V$			−120	mA
LVDS DRIVER DC SPECIFICATIONS						
V_{OD}	Differential Output Voltage	$R_L = 100\Omega$	250	290	450	mV
ΔV_{OD}	Change in V_{OD} between Complimentary Output States				35	mV
V_{CM}	Common Mode Voltage		1.1	1.25	1.375	V
ΔV_{CM}	Change in V_{CM} between Complimentary Output States				35	mV
V_{OH}	High Level Output Voltage			1.3	1.6	V
V_{OL}	Low Level Output Voltage		0.9	1.07		V
I_{OS}	Output Short Circuit Current	$V_{OUT} = 0V, R_L = 100\Omega$		−2.9	−5	mA
I_{OZ}	Output TRI-STATE® Current	Power Down = 0V, $V_{OUT} = 0V$ or V_{CC}		±1	±10	μA
LVDS RECEIVER DC SPECIFICATIONS						
V_{TH}	Differential Input High Threshold	$V_{CM} = +1.2V$			+100	mV
V_{TL}	Differential Input Low Threshold		−100			mV
I_{IN}	Input Current	$V_{IN} = +2.4V$	$V_{CC} = 5.5V$		±10	μA
		$V_{IN} = 0V$			±10	μA

Note 1: "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. They are not meant to imply that the device should be operated at these limits. The tables of "Electrical Characteristics" specify conditions for device operation.

Note 2: Typical values are given for $V_{CC} = 5.0V$ and $T_A = +25^\circ C$.

Note 3: Current into device pins is defined as positive. Current out of device pins is defined as negative. Voltages are referenced to ground unless otherwise specified (except V_{OD} and ΔV_{OD}).

Note 4: ESD Rating: HBM (1.5 kΩ, 100 pF)

PLL $V_{CC} \geq 1000V$

All other pins $\geq 2000V$

EIAJ (0Ω, 200 pF) $\geq 150V$

Electrical Characteristics (Continued)

Over recommended operating supply and temperature ranges unless otherwise specified

Symbol	Parameter	Conditions	Min	Typ	Max	Units
TRANSMITTER SUPPLY CURRENT						
I _{CCTW}	Transmitter Supply Current, Worst Case	R _L = 100Ω, C _L = 5 pF, Worst Case Pattern (Figures 1, 3)	f = 32.5 MHz		34	46 mA
			f = 37.5 MHz		36	48 mA
I _{CCTG}	Transmitter Supply Current, 16 Grayscale	R _L = 100Ω, C _L = 5 pF, Grayscale Pattern (Figures 2, 3)	f = 32.5 MHz		27	42 mA
			f = 37.5 MHz		28	43 mA
I _{CCTZ}	Transmitter Supply Current, Power Down	Power Down = Low		1	10	μA
RECEIVER SUPPLY CURRENT						
I _{CCRW}	Receiver Supply Current, Worst Case	C _L = 8 pF, Worst Case Pattern (Figures 1, 4)	f = 32.5 MHz		55	75 mA
			f = 37.5 MHz		60	80 mA
I _{CCRG}	Receiver Supply Current, 16 Grayscale	C _L = 8 pF, 16 Grayscale Pattern (Figures 2, 4)	f = 32.5 MHz		35	55 mA
			f = 37.5 MHz		37	58 mA
I _{CCRZ}	Receiver Supply Current, Power Down	Power Down = Low		1	10	μA

Switching Characteristics

Over recommended operating supply and temperature ranges unless otherwise specified

Symbol	Parameter	Min	Typ	Max	Units
LLHT	LVDS Low-to-High Transition Time (Figure 3)		0.75	1.5	ns
LHLT	LVDS High-to-Low Transition Time (Figure 3)		0.75	1.5	ns
CLHT	CMOS/TTL Low-to-High Transition Time (Figure 4)		3.5	6.5	ns
CHLT	CMOS/TTL High-to-Low Transition Time (Figure 4)		2.7	6.5	ns
TCIT	TxCLK IN Transition Time (Figure 5)			8	ns
TCCS	TxOUT Channel-to-Channel Skew (Note A) (Figure 6)			350	ps
TSSPW	Tx Sub-Symbol Pulse Width (Figure 6)	f = 20 MHz	5.5	7	8 ns
RCCS	RxIN Channel-to-Channel Skew (Note B)			700	ps
TCIP	TxCLK IN Period (Figure 7)	25	T	50	ns
TCIH	TxCLK IN High Time (Figure 7)	0.35T	0.5T	0.65T	ns
TCIL	TxCLK IN Low Time (Figure 7)	0.35T	0.5T	0.65T	ns
TSTC	TxIN Setup to TxCLK IN (Figure 7)	8			ns
THTC	TxIN Hold to TxCLK IN (Figure 7)	2.5	2		ns
RCOP	RxCLK OUT Period (Figure 8)	25	T	50	ns

Note A: This limit based on bench characterization.

Note B: This limit assumes a maximum cable skew of 350 ps.

Switching Characteristics

Over recommended operating supply and temperature ranges unless otherwise specified (Continued)

Symbol	Parameter		Min	Typ	Max	Units
RCOH	RxCLK OUT High Time (Figure 8)	f = 20 MHz	21.5			ns
		f = 40 MHz	10.5			ns
RCOL	RxCLK OUT Low Time (Figure 8)	f = 20 MHz	19			ns
		f = 40 MHz	6			ns
RSRC	RxOUT Setup to RxCLK OUT (Figure 8)	f = 20 MHz	14			ns
		f = 40 MHz	4.5			ns
RHRC	RxOUT Hold to RxCLK OUT (Figure 8)	f = 20 MHz	16			ns
		f = 40 MHz	6.5			ns
TCCD	TxCLK IN to TxCLK OUT Delay @ 25°C, V _{CC} = 5.0V (Figure 9)		5		9.7	ns
RCCD	RxCLK IN to RxCLK OUT Delay @ 25°C, V _{CC} = 5.0V (Figure 10)		7.6		11.9	ns
TPLLS	Transmitter Phase Lock Loop Set (Figure 11)				10	ms
RPLLS	Receiver Phase Lock Loop Set (Figure 12)				10	ms

AC Timing Diagrams




FIGURE 1. "WORST CASE" Test Pattern

TL/F/12486-15

Device Pin Name	Signal	Signal Pattern	Signal Frequency
TxCLK IN/RxCLK OUT	Dot Clk		f
TxIN0/RxOUT0	R7		1/16
TxIN1/RxOUT1	R6		1/8
TxIN2/RxOUT2	R5		1/4
TxIN3/RxOUT3	R4		1/2
TxIN4/RxOUT4	R3		Steady State, Low
TxIN5/RxOUT5	R2		Steady State, Low
TxIN6/RxOUT6	R1		Steady State, Low
TxIN7/RxOUT7	R0		Steady State, Low
TxIN8/RxOUT8	G7		1/16
TxIN9/RxOUT9	G6		1/8
TxIN10/RxOUT10	G5		1/4
TxIN11/RxOUT11	G4		1/2
TxIN12/RxOUT12	G3		Steady State, Low
TxIN13/RxOUT13	G2		Steady State, Low
TxIN14/RxOUT14	G1		Steady State, Low
TxIN15/RxOUT15	G0		Steady State, Low
TxIN16/RxOUT16	B7		1/16
TxIN17/RxOUT17	B6		1/8
TxIN18/RxOUT18	B5		1/4
TxIN19/RxOUT19	B4		1/2
TxIN20/RxOUT20	B3		Steady State, Low
TxIN21/RxOUT21	B2		Steady State, Low
TxIN22/RxOUT22	B1		Steady State, Low
TxIN23/RxOUT23	B0		Steady State, Low
TxIN24/RxOUT24	Sync1		Steady State, High
TxIN25/RxOUT25	Sync2		Steady State, High
TxIN26/RxOUT26	Sync3		Steady State, High
TxIN27/RxOUT27	Sync4		Steady State, High

FIGURE 2. "16 GRAYSCALE" Test Pattern


TL/F/12486-16

Note 1: The worst case test pattern produces a maximum toggling of digital circuits, LVDS I/O and CMOS/TTL I/O.


Note 2: The 16 grayscale test pattern tests device power consumption for a "typical" LCD display pattern. The test pattern approximates signal switching needed to produce groups of 16 vertical stripes across the display.

Note 3: Figure 1 and Figure 2 show a falling edge data strobe (TxCLK IN/RxCLK OUT).

AC Timing Diagrams (Continued)





$$V_{diff} = (TxOUT+) - (TxOUT-)$$




TL/F/12486-9

FIGURE 3. DS90CF581 (Transmitter) LVDS Output Load and Transition Timing




TL/F/12486-11

FIGURE 4. DS90CF582 (Receiver) CMOS/TTL Output Load and Transition Timing



TL/F/12486-17

FIGURE 5. DS90CF581 (Transmitter) Input Clock Transition Time



TL/F/12486-18


Note 1: Measurements at $V_{diff} = 0V$

Note 2: TCCS measured between earliest and latest initial LVDS edges.

Note 3: TxCLK OUT Differential High → Low Edge for DS90CF581
TxCLK OUT Differential Low → High Edge for DS90CR581


FIGURE 6. DS90CF581 (Transmitter) Channel-to-Channel Skew and Pulse Width

AC Timing Diagrams (Continued)




TL/F/12486-12

FIGURE 7. DS90CF581 (Transmitter) Setup/Hold and High/Low Times




TL/F/12486-13

FIGURE 8. DS90CF582 (Receiver) Setup/Hold and High/Low Times



TL/F/12486-19


FIGURE 9. DS90CF581 (Transmitter) Clock In to Clock Out Delay



TL/F/12486-20


FIGURE 10. DS90CF582 (Receiver) Clock In to Clock Out Delay

AC Timing Diagrams (Continued)



TL/F/12486-14

FIGURE 11. DS90CF581 (Transmitter) Phase Lock Loop Set Time



TL/F/12486-21

FIGURE 12. DS90CF582 (Receiver) Phase Lock Loop Set Time

AC Timing Diagrams (Continued)




FIGURE 13. Seven Bits of LVDS in One Block Cycle

TL/F/12486-22




FIGURE 14. 28 Parallel TTL Data Inputs Mapped to LVDS Outputs (DS90CF581)

TL/F/12486-23

DS90CF581 Pin Description—FPD Link Transmitter

Pin Name	I/O	No.	Description
TxIN	I	28	TTL level input. This includes: 8 Red, 8 Green, 8 Blue, and 4 control lines (FPLINE, FPFRAME, DRDY, CNTL). (Also referred to as HSYNC, VSYNC and DATA ENABLE)
TxOUT +	O	4	Positive LVDS differential data output
TxOUT –	O	4	Negative LVDS differential data output
FPSHIFT IN	I	1	TTL level clock input. The falling edge acts as data strobe.
TxCLK OUT +	O	1	Positive LVDS differential clock output
TxCLK OUT –	O	1	Negative LVDS differential clock output
PWR DOWN	I	1	TTL level input. Assertion (low input) TRI-STATE the outputs, ensuring low current at power down.
V _{CC}	I	4	Power supply pins for TTL inputs
GND	I	5	Ground pins for TTL inputs
PLL V _{CC}	I	1	Power supply pin for PLL
PLL GND	I	2	Ground pins for PLL
LVDS V _{CC}	I	1	Power supply pin for LVDS outputs
LVDS GND	I	3	Ground pins for LVDS outputs

DS90CF582 Pin Description—FPD Link Receiver

Pin Name	I/O	No.	Description
RxIN +	I	4	Positive LVDS differential data inputs.
RxIN –	I	4	Negative LVDS differential data inputs.
RxOUT	O	28	TTL level data outputs. This includes: 8 Red, 8 Green, 8 Blue, and 4 control lines (FPLINE, FPFRAME, DRDY, CNTL). (Also referred to as HSYNC, VSYNC and DATA ENABLE)
RxCLK IN +	I	1	Positive LVDS differential clock input
RxCLK IN –	I	1	Negative LVDS differential clock input
FPSHIFT OUT	O	1	TTL level clock output. The falling edge acts as data strobe.
PWR DOWN	I	1	TTL level input. Assertion (low input) TRI-STATE the outputs, ensuring low current at power down.
V _{CC}	I	4	Power supply pins for TTL outputs
GND	I	5	Ground pins for TTL outputs
PLL V _{CC}	I	1	Power supply pin for PLL
PLL GND	I	2	Ground pin for PLL
LVDS V _{CC}	I	1	Power supply pin for LVDS inputs
LVDS GND	I	3	Ground pins for LVDS inputs