

□ MN101D07H

VTR Servo

Type	MN101D07H	
ROM (x8-bit)	160 K	
RAM (x8-bit)	5 K	
Package	LQFP112-P-2020 *Lead-free	
Minimum Instruction Execution Time	With main clock operated	0.1397 μs (at 4.0 V to 5.5 V, 14.32 MHz)
	When sub-clock operated	71.5 μs (at 3.0 V to 5.5 V fixed to 14.32 MHz internal frequency division)
		61 μs (at 2.2 V to 5.5 V, 32.768 kHz)
Interrupts	<ul style="list-style-type: none"> • RESET • Runaway • External 0, 1, 2, 3, 4/key input (P50 to 54) • Timer 0 • Timer 1 • Timer 2 • Timer 3 • Timer 4 • Timer 6 • Capstan FG • Control • HSW • Cylinder FG • Servo VSYNC • Synchronous output • OSD • XDS • Serial 0 • Serial 1 • Serial 2 • A/D (common with PWM 4 reference frequency) • OSDVSYNC 	
Timer Counter	<p>Timer counter 0: 16-bit × 1 (timer function, clock function [max. 2 s or max. 36 h at cascade-connecting with timer 6]) Clock source 1/2, 1/4, 1/8, 1/16 of system clock frequency; overflow of timer counter 6; 1/512 of XI oscillation clock or OSC oscillation clock frequency Interrupt source overflow of timer counter 0</p> <p>Timer counter 1: 16-bit × 1 (timer function, linear timer counter function) Clock source 1/2, 1/4, 1/8, 1/16 of system clock frequency; CTL signal Interrupt source overflow of timer counter 1</p> <p>Timer counter 2: 16-bit × 1 (timer function, input capture (DCTL specified edge), duty judgment of DCTL signal) Clock source 1/2, 1/4, 1/8, 1/12, 1/16, 1/24 of system clock frequency Interrupt source overflow of timer counter 2; input of DCTL specified edge; underflow of timer 2 shift register 4-bit counter; coincidence of timer 2 shift register with timer 2 shift register compare register</p> <p>Timer counter 3: 16-bit × 1 (timer function, detection of serial indexing, generation of remote control output carrier frequency) Clock source 1/2, 1/4, 1/8, 1/16 of system clock frequency; XI oscillation clock Interrupt source overflow of timer counter 3</p> <p>Timer counter 4: 16-bit × 1 (timer function, event count [P15 input], generation of serial transmission clock) Clock source 1/8, 1/16 of system clock frequency; external clock input Interrupt source overflow of timer counter 4; coincidence of timer counter 4 with OCR4</p> <p>Timer counter 5: 19-bit × 1 (watchdog, stable oscillation waiting function) Clock source system clock Watchdog interrupt source .. 1/2¹⁶, 1/2¹⁹ of timer counter 5 frequency Clear by stable oscillation .. after 256 counts by timer counter 5 (2¹⁸ counts of OSC oscillation clock)</p> <p>Timer counter 6: 16-bit × 1 (clock function [max. 2 s]) Clock source 1/512 of OSC oscillation clock frequency; XI oscillation clock; 1/4, 1/8, 1/64, 1/128 of system clock frequency Interrupt source 1/2¹³, 1/2¹⁴, 1/2¹⁵ overflow of timer counter 6</p> <p>Timer counter 7: 8-bit × 1 (timer function, event count [P53 input]) Clock source 1/4, 1/8, 1/16, 1/32 of system clock frequency; external clock input Interrupt source overflow of timer counter 7</p>	
Serial Interface	<p>Serial 0: 8-bit × 1 (synchronous type/start-stop synchronous type) (transfer direction of MSB/LSB selectable) Synchronous type clock source · 1/4, 1/8, 1/16, 1/32, 1/64, 1/128, 1/256 of system clock frequency; 2-division timer 4 output; SBT0 pin input Clock for UART 8-division of above clock; 2-division timer 4 output; SBT0 pin input</p>	

Serial Interface (Continue)

Serial 1: 8-bit × 1
 (synchronous type/remote control transmission/simple remote control receive) (transfer direction of MSB/LSB selectable, start condition function)
 Clock source 1/8, 1/16, 1/32, 1/64, 1/128, 1/256 of system clock frequency;
 2-division timer 4 output; SBT1 pin input
 Remote control clock 2-division timer 4 output

Serial 2: 8-bit × 1 (I²C) (master transmission/reception, slave transmission/reception)
 Clock source 1/144 to 1/252 of system clock, SCK pin input

OSD

OSD mode: Accommodation with menu or super impose display

Applicable broadcasting system : NTSC, PAL, PAL-M, PAL-N

Screen configuration : 24 characters × 2n rows (n = 1 to 6)

Character type : max. 512 character types (variable)

Character size : 12 × 18 dots

Enlarged characters : each × 2, × 3 or × 4 settings in horizontal and vertical

Character interpolation : none

Line background color : 8-hue settable (settable in the row unit at menu display)

Line background intensity : 8 gradations settable in the row unit

Screen background color : 8-hue settable (at output of composite video signal)

Character color : white

Character intensity : 8 gradations settable in the row unit

Frame function : 1-dot frame in 4 or 8 directions

Frame intensity : 4 gradations settable in the row unit

Box shade function : settable in the character unit (at output of composite video signal with 129 or more characters (character types))

Blinking : none (covered by software)

Inverted character : settable in the character unit

Halftone : settable in the row unit in 2 intensity gradations (at output of external synchronous composite video signal)

CCD mode: Supports Closed Caption in the U.S.A.

Screen configuration : 32 characters × 16 rows

Character type : max. 128 character types (variable)

Character size : 12 × 26 dots (including 8 dots in the underlined area)

Enlarged characters : none

Character interpolation : none

Line background color : 8-hue settable

Line background intensity : 8 gradations settable in the screen unit (at output of composite video signal)

Screen background color : 8-hue settable (at output of composite video signal)

Character color : 8 colors (at RGB output)
 : White (at output of composite video signal)

Character intensity : 8 gradations settable in the screen unit

Frame function : none

Box shade function : none

Inverted character : none

Halftone : settable in the row unit in 2 intensity gradations
 (at output of external synchronous composite video signal)

Others : Underline, italic, blinking function and scroll

Input : composite video signal input (output level: 1 V_[p-p] / 2 V_[p-p])

Clamp method : sync chip clamp, clamp level in 4 levels

Output : composite video output
 : output of Y/C split video signal
 : digital output (6 pins)

Measure against image fluctuation : built-in AFC circuit

Dot clock : 1/2 of OSC oscillation clock (automatic phase adjustment)

See the next page for electrical characteristics, pin assignment and support tool.

XDS	Built-in U.S. closed caption data slicer (optional 2 line data can be extracted.)		
ROM Correction	Correcting address designation: up to 3 addresses possible Correction method: correction program being saved in internal RAM		
I/O Pins	I/O	85	• Common use: 85 ports 0, 1, 2, 4, 5, 6, 7, A, B (by bit)
	Input	2	• Common use: 2
A/D Inputs	8-bit × 13-ch. (without S/H)		
PWM	13-bit × 2-ch. (at repetition cycle 572 μs, 14.32 MHz), 10-bit × 2-ch. (at repetition cycle 71.5 μs, 14.32 MHz), 8-bit × 1-ch. (at repetition cycle 35.7 μs, 14.32 MHz)		
ICR	18-bit × 6-ch.		
OCR	16-bit × 7-ch. , 8-bit × 1-ch.		
Special Ports	Buzzer output; 3-state output (PTO) VLP pin; synchronous output: 7; 3-state synchronous output: 4; remote control receive; CTL amp; built-in FG amp; output of 1/2 OSC oscillation clock (2 V[p-p]); output of 1/4 OSC oscillation clock (1 V[p-p])		
Notes	VISS/VASS detection function		

Electrical Characteristics

Supply current

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Operating supply current	IDD1	14.32 MHz operation without load, VDD = 5 V		60	100	mA
	IDD2	1/1024 of 14.32 MHz operation without load, VDD = 3.0 V		2	5	mA
	IDD3	Stop of 14.32 MHz oscillation, VDD = 2.7 V 32 kHz oscillation operation without load		50	100	μA
Supply current at STOP	IDSP	Stop of oscillation without load, VDD = 5 V			20	μA
Supply current at HALT	IDHT0	14.32 MHz oscillation without load, VDD = 5 V		5	15	mA
	IDHT1	Stop of 14.32 MHz oscillation, VDD = 2.7 V 32 kHz oscillation operation without load		5	20	μA


(Ta = 25°C ± 2°C, VSS = 0 V)

A/D Converter Performance

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Conversion relative error	ΔNLAD				± 3	LSB
A/D Conversion Time	tAD	fosc = 14.32 MHz		8		μs
Analog Input Voltage					5	V

(Ta = 25°C ± 2°C, VSS = 0 V)

Pin Assignment



LQFP112-P-2020 *Lead-free

Support Tool

In-circuit Emulator	PX-ICE101C / D + PX-PRB101D07-LQFP112-P-2020-M	
Flash Memory Built-in Type	Type	MN101DF07K [ES (Engineering Sample) available]
	ROM (× 8-bit)	224 K
	RAM (× 8-bit)	6 K
	Minimum instruction execution time	0.1397 μs (at 4.0 V to 5.5 V, 14.32 MHz) 71.5 μs (at 3.0 V to 5.5 V, fixed to 14.32 MHz internal division)
	Package	LQFP112-P-2020 *Lead-free

Request for your special attention and precautions in using the technical information and semiconductors described in this material

- (1) An export permit needs to be obtained from the competent authorities of the Japanese Government if any of the products or technologies described in this material and controlled under the "Foreign Exchange and Foreign Trade Law" is to be exported or taken out of Japan.
- (2) The technical information described in this material is limited to showing representative characteristics and applied circuits examples of the products. It neither warrants non-infringement of intellectual property right or any other rights owned by our company or a third party, nor grants any license.
- (3) We are not liable for the infringement of rights owned by a third party arising out of the use of the product or technologies as described in this material.
- (4) The products described in this material are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (5) The products and product specifications described in this material are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (6) When designing your equipment, comply with the guaranteed values, in particular those of maximum rating, the range of operating power supply voltage, and heat radiation characteristics. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (7) When using products for which damp-proof packing is required, observe the conditions (including shelf life and amount of time let standing of unsealed items) agreed upon when specification sheets are individually exchanged.
- (8) This material may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.