

Advance Information

MPC7410RXNEPNS/D
Rev. 1, 10/2002

MPC7410 Part Number
Specification for the
MPC7410RXnnnNE Series



digital dna[™]

Motorola Part Numbers Affected:

*MPC7410RX400NE
MPC7410RX450NE*

This document describes part-number-specific changes to recommended operating conditions and revised electrical specifications, as applicable, from those described in the general *MPC7410 Hardware Specifications* (order #: MPC7410EC/D).

Specifications provided in this document supersede those in the *MPC7410 Hardware Specifications*, for the part numbers listed in Table A only. Specifications not addressed herein are unchanged. Because this document is frequently updated, refer to <http://www.motorola.com/semiconductors> or to your Motorola sales office for the latest version.

Note that headings and table numbers in this document are not consecutively numbered. They are intended to correspond to the heading or table affected in the general hardware specification. Part numbers addressed in this document are listed in Table A. For more detailed ordering information, see Table 17.

Features

Table A. Part Numbers Addressed by this Data Sheet

Motorola Part Number	Operating Conditions				Significant Differences from Hardware Specification
	CPU Frequency	Vdd	T _J (°C)	OVdd	
MPC7410RX400NE	400 MHz	1.5V±50mV	0 to 105	1.8/2.5 V	Reduced core voltage to achieve lower power consumption. Removes 3.3V OVdd support. For all AC/DC specifications not mentioned in this document, please refer to the MPC7410RX400LE specifications in the general <i>MPC7410 Hardware Specifications</i> .
	450 MHz	1.8V ±100mV	0 to 105	1.8/2.5/3.3 V	The MPC7410RX400NE also fully conforms to the MPC7410RX450LE specification. Refer to the general <i>MPC7410 Hardware Specifications</i> .
MPC7410RX450NE	450 MHz	1.5V±50mV	0 to 105	1.8/2.5 V	Reduced core voltage to achieve lower power consumption. Removes 3.3V OVdd support. For all AC/DC specifications not mentioned in this document, please refer to the MPC7410RX450LE specifications in the general <i>MPC7410 Hardware Specifications</i> .
	500 MHz	1.8V ±100mV	0 to 105	1.8/2.5/3.3 V	The MXPC7410RX450NE also fully conforms to the MPC7410RX500LE specification. Refer to the general <i>MPC7410 Hardware Specifications</i> .

1.2 Features

This section summarizes changes to the features of the MPC7410 described in the *MPC7410 Hardware Specifications*.

- Bus interface
 - Selectable interface voltages of 1.8 V, 2.5 V (3.3 V not supported)

1.4.1 DC Electrical Characteristics

Voltage to the L2 I/Os and processor interface I/Os are provided through separate sets of supply pins and may be provided at the voltages shown in Table 2.

Table 2. Input Threshold Voltage Setting

BVSEL Signal ³	Processor Bus Input Threshold is Relative to:	L2VSEL Signal ³	L2 Bus Input Threshold is Relative to:	Note
0	1.8 V	0	1.8 V	1
$\overline{\text{HRESET}}$	2.5 V	$\overline{\text{HRESET}}$	2.5 V	1, 2
1	Not Supported	1	2.5 V	1, 4, 5
$\overline{\text{HRESET}}$	Not Supported	$\overline{\text{HRESET}}$	Not Supported	

Notes:

- Caution:** The input threshold selection must agree with the OVdd/L2OVdd voltages supplied.
- To select the 2.5-V threshold option, BVSEL and/or L2VSEL should be tied to $\overline{\text{HRESET}}$ so that the two signals change state together. This is the preferred method for selecting this mode of operation.
- To overcome the internal pull-up resistance, a pull-down resistance less than 250 ohms should be used.
- Default voltage setting if left unconnected (internal pulled-up).
- Caution:** The XPC7410RXnnnNE does not support the default OVdd setting of 3.3 V. The BVSEL input must be tie either low or to $\overline{\text{HRESET}}$.

Table 3 provides the recommended operating conditions for the MPC7410 part numbers described herein.

Table 3. Recommended Operating Conditions

Characteristic		Symbol	Recommended Value	Unit
Core supply voltage		Vdd	1.5V ± 50mV	V
PLL supply voltage		AVdd	1.5V ± 50mV	V
L2 DLL supply voltage		L2AVdd	1.5V ± 50mV	V
Processor bus supply voltage	BVSEL = 0	OVdd	1.8V ± 100mV	V
	$\overline{\text{BVSEL}} = \overline{\text{HRESET}}$	OVdd	2.5V ± 100mV	V
	BVSEL = $\overline{\text{HRESET}}$ or BVSEL = 1	OVdd	Not Supported	V
L2 bus supply voltage	L2VSEL = 0	L2OVdd	1.8V ± 100mV	V
	$\overline{\text{L2VSEL}} = \overline{\text{HRESET}}$ or L2VSEL = 1	L2OVdd	2.5V ± 100mV	V
Input voltage	Processor bus and JTAG Signals	V _{in}	GND to OVdd	V
	L2 Bus	V _{in}	GND to L2OVdd	V
Die-junction temperature		T _j	0-105	°C
Note: These are the recommended and tested operating conditions. Proper device operation outside of these conditions is not guaranteed.				

Table 7 provides the power consumption for the MPC7410 part at the frequencies described herein.

Table 7. Power Consumption for MPC7410

	Processor (CPU) Frequency	Processor (CPU) Frequency	Unit	Notes
	400Mhz	450Mhz		
Full-On Mode				
Typical	2.92	3.29	W	1, 3
Maximum	6.6	7.43	W	1, 2,
Doze Mode				
Maximum	3.6	4.1	W	1, 2
Nap Mode				
Maximum	1.35	1.5	W	1, 2
Sleep Mode				
Maximum	1.3	1.45	W	1, 2
Sleep Mode—PLL and DLL Disabled				
Typical	0.6	0.6	W	1, 3
Maximum	1.1	1.1	W	1, 2

Notes:

1. These values apply for all valid processor bus and L2 bus ratios. The values do not include I/O Supply Power (OVdd and L2OVdd) or PLL/DLL supply power (AVdd and L2AVdd). OVdd and L2OVdd power is system dependent, but is typically <10% of Vdd power. Worst case power consumption for AVdd = 15 mw and L2AVdd = 15 mW.
2. Maximum power is measured at 105 °C and Vdd = 1.5V while running an entirely cache-resident, contrived sequence of instructions which keep the execution units, including AltiVec, maximally busy.
3. Typical power is an average value measured at 65 °C and Vdd = 1.5V in a system while running typical benchmarks.

1.9 Document Revision History

Table 16 provides a revision history for this Part Number Specification.

Table 16. Document Revision History

Document Revision	Substantive Changes
Rev 0	Initial Release
Rev 1	Minor formatting
	Added Section 1.9 Document Revision History
	Section 1.10.1 - added Table 17 - Part-Marking Nomenclature

1.10 Ordering Information

1.10.1 Part Numbers Addressed by this Specification

Table 17 provides the ordering information for the MPC7410 part described in this document.

Table 17. Part-Marking Nomenclature


Product Code	Part Identifier	Package	Processor Frequency ¹	Application Modifier	Revision Level
MPC	7410	RX = CBGA	400 450	N: 1.5 V ± 50 mV 0 to 105 °C	E: 1.4; PVR = 800C 1104

Notes:

1. Processor core frequencies supported by parts addressed by this specification only. Parts addressed by other specifications may support other maximum core frequencies.

1.10.3 Part Marking

Parts are marked as the example shown in Figure 26.



Notes:

nnn is the speed grade of the part
 MMMMMM is the 6-digit mask number
 ATWLYYWWA is the traceability code
 CCCCC is the country of assembly (this space is left blank if parts are assembled in the United States)

Figure 26. Motorola Part Marking for BGA Device

HOW TO REACH US:**USA/EUROPE/LOCATIONS NOT LISTED:**

Motorola Literature Distribution
P.O. Box 5405, Denver, Colorado 80217
1-303-675-2140 or 1-800-441-2447

JAPAN:

Motorola Japan Ltd.
SPS, Technical Information Center
3-20-1, Minami-Azabu Minato-ku
Tokyo 106-8573 Japan
81-3-3440-3569

ASIA/PACIFIC:

Motorola Semiconductors H.K. Ltd.
Silicon Harbour Centre, 2 Dai King Street
Tai Po Industrial Estate, Tai Po, N.T., Hong Kong
852-26668334

TECHNICAL INFORMATION CENTER:

1-800-521-6274

HOME PAGE:

<http://www.motorola.com/semiconductors>

DOCUMENT COMMENTS:

FAX (512) 933-2625
Attn: RISC Applications Engineering

Information in this document is provided solely to enable system and software implementers to use Motorola products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Motorola reserves the right to make changes without further notice to any products herein.

Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part.



Motorola and the Stylized M Logo are registered in the U.S. Patent and Trademark Office. digital dna is a trademark of Motorola, Inc. All other product or service names are the property of their respective owners. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

© Motorola, Inc. 2002

MPC7410RXNEPNS/D