

# BC846, SBC846, BC847, SBC847, BC848 Series

## General Purpose Transistors

### NPN Silicon

These transistors are designed for general purpose amplifier applications. They are housed in the SC-70/SOT-323 which is designed for low power surface mount applications.

#### Features

- AEC-Q101 Qualified and PPAP Capable
- S Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements
- These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

#### MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-Emitter Voltage BC846, SBC846 BC847, SBC847 BC848	$V_{CEO}$	65 45 30	V
Collector-Base Voltage BC846, SBC846 BC847, SBC847 BC848	$V_{CBO}$	80 50 30	V
Emitter-Base Voltage BC846, SBC846 BC847, SBC847 BC848	$V_{EBO}$	6.0 6.0 5.0	V
Collector Current – Continuous	$I_C$	100	mAdc

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

#### THERMAL CHARACTERISTICS



Characteristic	Symbol	Max	Unit
Total Device Dissipation FR-5 Board, (Note 1) $T_A = 25^\circ\text{C}$	$P_D$	150	mW
Thermal Resistance, Junction-to-Ambient	$R_{\theta JA}$	833	$^\circ\text{C}/\text{W}$
Junction and Storage Temperature	$T_J, T_{stg}$	-55 to +150	$^\circ\text{C}$

1. FR-5 = 1.0 x 0.75 x 0.062 in.




ON Semiconductor®

<http://onsemi.com>



#### MARKING DIAGRAM



XX = Specific Device Code

M = Month Code

▪ = Pb-Free Package

(Note: Microdot may be in either location)

#### ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 12 of this data sheet.

# BC846, SBC846, BC847, SBC847, BC848 Series

**ELECTRICAL CHARACTERISTICS** ( $T_A = 25^\circ\text{C}$  unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
<b>OFF CHARACTERISTICS</b>					
Collector – Emitter Breakdown Voltage ( $I_C = 10 \text{ mA}$ )	$V_{(\text{BR})\text{CEO}}$	65 45 30	– – –	– – –	V
Collector – Emitter Breakdown Voltage ( $I_C = 10 \mu\text{A}$ , $V_{EB} = 0$ )	$V_{(\text{BR})\text{CES}}$	80 50 30	– – –	– – –	V
Collector – Base Breakdown Voltage ( $I_C = 10 \mu\text{A}$ )	$V_{(\text{BR})\text{CBO}}$	80 50 30	– – –	– – –	V
Emitter – Base Breakdown Voltage ( $I_E = 1.0 \mu\text{A}$ )	$V_{(\text{BR})\text{EBO}}$	6.0 6.0 5.0	– – –	– – –	V
Collector Cutoff Current ( $V_{CB} = 30 \text{ V}$ ) ( $V_{CB} = 30 \text{ V}$ , $T_A = 150^\circ\text{C}$ )	$I_{CBO}$	– –	– –	15 5.0	nA $\mu\text{A}$

## ON CHARACTERISTICS


DC Current Gain ( $I_C = 10 \mu\text{A}$ , $V_{CE} = 5.0 \text{ V}$ )	BC846A, BC847A, SBC847A, BC848A BC846B, SBC846B, BC847B, SBC847B, BC848B BC847C, SBC847C, BC848C	$h_{FE}$	– – –	90 150 270	– – –
( $I_C = 2.0 \text{ mA}$ , $V_{CE} = 5.0 \text{ V}$ )	BC846A, BC847A, SBC847A, BC848A BC846B, SBC846B, BC847B, SBC847B, BC848B BC847C, SBC847C, BC848C		110 200 420	180 290 520	220 450 800
Collector – Emitter Saturation Voltage ( $I_C = 10 \text{ mA}$ , $I_B = 0.5 \text{ mA}$ ) ( $I_C = 100 \text{ mA}$ , $I_B = 5.0 \text{ mA}$ )	$V_{CE(\text{sat})}$	– –	– –	0.25 0.6	V
Base – Emitter Saturation Voltage ( $I_C = 10 \text{ mA}$ , $I_B = 0.5 \text{ mA}$ ) ( $I_C = 100 \text{ mA}$ , $I_B = 5.0 \text{ mA}$ )	$V_{BE(\text{sat})}$	– –	0.7 0.9	– –	V
Base – Emitter Voltage ( $I_C = 2.0 \text{ mA}$ , $V_{CE} = 5.0 \text{ V}$ ) ( $I_C = 10 \text{ mA}$ , $V_{CE} = 5.0 \text{ V}$ )	$V_{BE(\text{on})}$	580 –	660 –	700 770	mV

## SMALL-SIGNAL CHARACTERISTICS


Current – Gain – Bandwidth Product ( $I_C = 10 \text{ mA}$ , $V_{CE} = 5.0 \text{ Vdc}$ , $f = 100 \text{ MHz}$ )	$f_T$	100	–	–	MHz
Output Capacitance ( $V_{CB} = 10 \text{ V}$ , $f = 1.0 \text{ MHz}$ )	$C_{obo}$	–	–	4.5	pF
Noise Figure ( $I_C = 0.2 \text{ mA}$ , $V_{CE} = 5.0 \text{ Vdc}$ , $R_S = 2.0 \text{ k}\Omega$ , $f = 1.0 \text{ kHz}$ , $BW = 200 \text{ Hz}$ )	NF	–	–	10	dB

# BC846, SBC846, BC847, SBC847, BC848 Series


## BC846A, BC847A, SBC847A, BC848A




**Figure 1. DC Current Gain vs. Collector Current**



**Figure 2. Collector Emitter Saturation Voltage vs. Collector Current**




**Figure 3. Base Emitter Saturation Voltage vs. Collector Current**




**Figure 4. Base Emitter Voltage vs. Collector Current**

# BC846, SBC846, BC847, SBC847, BC848 Series


## BC846A, BC847A, SBC847A, BC848A




**Figure 5. Collector Saturation Region**



**Figure 6. Base-Emitter Temperature Coefficient**



**Figure 7. Capacitances**



**Figure 8. Current-Gain - Bandwidth Product**

# BC846, SBC846, BC847, SBC847, BC848 Series

## BC846B, SBC846B




Figure 9. DC Current Gain vs. Collector Current




Figure 10. Collector Emitter Saturation Voltage vs. Collector Current




Figure 11. Base Emitter Saturation Voltage vs. Collector Current






Figure 12. Base Emitter Voltage vs. Collector Current

# BC846, SBC846, BC847, SBC847, BC848 Series


## BC846B, SBC846B




**Figure 13. Collector Saturation Region**



**Figure 14. Base-Emitter Temperature Coefficient**



**Figure 15. Capacitance**



**Figure 16. Current-Gain - Bandwidth Product**

# BC846, SBC846, BC847, SBC847, BC848 Series

## BC847B, SBC847B, BC848B




Figure 17. DC Current Gain vs. Collector Current




Figure 18. Collector Emitter Saturation Voltage vs. Collector Current




Figure 19. Base Emitter Saturation Voltage vs. Collector Current






Figure 20. Base Emitter Voltage vs. Collector Current

# BC846, SBC846, BC847, SBC847, BC848 Series


## BC847B, SBC847B, BC848B




**Figure 21. Collector Saturation Region**



**Figure 22. Base-Emitter Temperature Coefficient**



**Figure 23. Capacitances**



**Figure 24. Current-Gain - Bandwidth Product**

# BC846, SBC846, BC847, SBC847, BC848 Series

## BC847C, SBC847C, BC848C




Figure 25. DC Current Gain vs. Collector Current




Figure 26. Collector Emitter Saturation Voltage vs. Collector Current




Figure 27. Base Emitter Saturation Voltage vs. Collector Current






Figure 28. Base Emitter Voltage vs. Collector Current

# BC846, SBC846, BC847, SBC847, BC848 Series


## BC847C, SBC847C, BC848C




**Figure 29. Collector Saturation Region**



**Figure 30. Base-Emitter Temperature Coefficient**




**Figure 31. Capacitances**




**Figure 32. Current-Gain - Bandwidth Product**


## BC846, SBC846, BC847, SBC847, BC848 Series



**Figure 33. Safe Operating Area for  
BC846A, BC846B**



**Figure 34. Safe Operating Area for  
BC847A, BC847B, BC847C**



**Figure 35. Safe Operating Area for  
BC848A, BC848B, BC848C**

## **BC846, SBC846, BC847, SBC847, BC848 Series**

### **DEVICE ORDERING AND SPECIFIC MARKING INFORMATION**

<b>Device</b>	<b>Specific Marking Code</b>	<b>Package</b>	<b>Shipping<sup>†</sup></b>
BC846AWT1G	1A	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
BC846BWT1G	1B	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
SBC846BWT1G			
BC847AWT1G	1E	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
SBC847AWT1G			
BC847BWT1G	1F	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
SBC847BWT1G			
BC847CWT1G	1G	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
SBC847CWT1G			
BC847CWT3G	1G	SC-70 (SOT-323) (Pb-Free)	10,000 / Tape & Reel
BC848AWT1G	1J	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
BC848BWT1G	1K	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel
BC848CWT1G	1L	SC-70 (SOT-323) (Pb-Free)	3,000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.


# BC846, SBC846, BC847, SBC847, BC848 Series

## PACKAGE DIMENSIONS

### SC-70 (SOT-323)

CASE 419-04

ISSUE N




NOTES:  
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.  
2. CONTROLLING DIMENSION: INCH.

DIM	MILLIMETERS			INCHES		
	MIN	NOM	MAX	MIN	NOM	MAX
A	0.80	0.90	1.00	0.032	0.035	0.040
A1	0.00	0.05	0.10	0.000	0.002	0.004
A2	0.70	REF		0.028	REF	
b	0.30	0.35	0.40	0.012	0.014	0.016
c	0.10	0.18	0.25	0.004	0.007	0.010
D	1.80	2.10	2.20	0.071	0.083	0.087
E	1.15	1.24	1.35	0.045	0.049	0.053
e	1.20	1.30	1.40	0.047	0.051	0.055
e1	0.65	BSC		0.026	BSC	
L	0.20	0.38	0.56	0.008	0.015	0.022
H_E	2.00	2.10	2.40	0.079	0.083	0.095

STYLE 3:  
PIN 1. BASE  
2. Emitter  
3. Collector

### SOLDERING FOOTPRINT\*



SCALE 10:1 (mm)  
(inches)

\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

**ON Semiconductor** and **ON** are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## PUBLICATION ORDERING INFORMATION

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor  
P.O. Box 5163, Denver, Colorado 80217 USA  
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada  
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada  
Email: [orderlit@onsemi.com](mailto:orderlit@onsemi.com)

### N. American Technical Support: 800-282-9855 Toll Free

USA/Canada

### Europe, Middle East and Africa Technical Support:

Phone: 421 33 790 2910

### Japan Customer Focus Center

Phone: 81-3-5817-1050

### ON Semiconductor Website: [www.onsemi.com](http://www.onsemi.com)

### Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local Sales Representative