

2N4048



PNP germanium power transistors designed for high-current applications requiring high gain and extremely low saturation voltage.

Collector connected to case

MAXIMUM RATINGS

Rating	Symbol		Unit
Collector-Emitter Voltage	V_{CEO}	30	Vdc
Collector-Emitter Voltage	V_{CES}	45	Vdc
Collector-Base Voltage	V_{CB}	45	Vdc
Emitter-Base Voltage	V_{EB}	25	Vdc
Collector Current - Continuous	I_C^*	← 60 →	Adc
Total Device Dissipation @ $T_C = 25^\circ C$ Derate above $25^\circ C$	P_D	← 170 → ← 2.0 →	Watts W/ $^\circ C$
Operating and Storage Junction Temperature Range	T_J, T_{stg}	-65 to +110	$^\circ C$

ELECTRICAL CHARACTERISTICS ($T_c = 25^\circ C$ unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit
----------------	--------	-----	-----	------

OFF CHARACTERISTICS

Collector-Emitter Breakdown Voltage† ($I_C = 1.0$ Adc, $I_E = 0$)	BV_{CEO}^\dagger	30	-	Vdc
Collector-Emitter Breakdown Voltage ($I_C = 300$ mAdc, $V_{BE} = 0$)	BV_{CES}	45	-	Vdc
Floating Potential ($V_{CB} = 45$ Vdc, $I_E = 0$)	V_{EBF}	-	0.5	Vdc
Collector Cutoff Current ($V_{CE} = 30$ Vdc, $V_{BE(off)} = 2.0$ Vdc, $T_C = +71^\circ C$)	I_{CEX}	-	15	mAdc
Collector Cutoff Current ($V_{CB} = 2.0$ Vdc, $I_E = 0$) ($V_{CB} = 45$ Vdc, $I_E = 0$)	I_{CBO}	-	0.2 4.0	mAdc
Emitter Cutoff Current ($V_{BE} = 25$ Vdc, $I_C = 0$) ($V_{BE} = 25$ Vdc, $I_C = 0$, $T_C = +71^\circ C$)	I_{EBO}	-	4.0 15	mAdc

ON CHARACTERISTICS

DC Current Gain† ($I_C = 15$ Adc, $V_{CE} = 2.0$ Vdc) ($I_C = 60$ Adc, $V_{CE} = 2.0$ Vdc)	h_{FE}^\dagger	60 15	180 -	-
Collector-Emitter Saturation Voltage† ($I_C = 15$ Adc, $I_B = 1.0$ Adc) ($I_C = 60$ Adc, $I_B = 6.0$ Adc)	$V_{CE(sat)}^\dagger$	-	0.15 0.3	Vdc
Base-Emitter Saturation Voltage† ($I_C = 15$ Adc, $I_B = 1.0$ Adc) ($I_C = 60$ Adc, $I_B = 6.0$ Adc)	$V_{BE(sat)}^\dagger$	-	0.6 1.0	Vdc

SMALL SIGNAL CHARACTERISTICS

Common-Emitter Cutoff Frequency ($I_C = 15$ Adc, $V_{CE} = 2.0$ Vdc)	f_{ce}	2.0	-	kHz
--	----------	-----	---	-----

† To avoid excessive heating of the collector junction, perform test with pulse method.