

September 1989 Revised August 2000

100313

Low Power Quad Driver

General Description

The 100313 is a monolithic quad driver with two OR and two NOR outputs and common enable. The common input is buffered to minimize input loading. If the D inputs are not used the Enable can be used to drive sixteen 50Ω lines. All inputs have $50~k\Omega$ pull-down resistors and all outputs are buffered.

Features


- 50% power reduction of the 100113
- 2000V ESD protection
- Pin/function compatible with 100113 and 100112
- Voltage compensated operating range = -4.2V to -5.7V
- Available to industrial grade temperature range (PLCC package only)

Ordering Code:

Order Number	Package Number	Package Description
100313SC	M24B	24-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-013, 0.300 Wide
100313PC	N24E	24-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-010, 0.400 Wide
100313QC	V28A	28-Lead Plastic Lead Chip Carrier (PLCC), JEDEC MO-047, 0.450 Square
100313QI		28-Lead Plastic Lead Chip Carrier (PLCC), JEDEC MO-047, 0.450 Square Industrial Temperature Range (-40°C to +85°C)

Devices also available in Tape and Reel. Specify by appending the suffix letter "X" to the ordering code.

Logic Symbol




Pin Descriptions

Pin Names	Description						
D _a –D _d	Data Inputs						
E	Enable Input						
O _{na} -O _{nd}	Data Outputs						
\overline{O}_{na} – \overline{O}_{nd}	Complementary Data Outputs						

Connection Diagrams



28-Pin PLCC



Truth Table

Inputs					Outputs								
E	Da	D _b	D _c	D _d	O _{1a} , O _{2a}	$\overline{O}_{1a}, \overline{O}_{2a}$	O _{1b} , O _{2b}	0 _{1b} , 0 _{2b}	O _{1c} , O _{2c}	O _{1c} , 0 _{2c}	O _{1d} , O _{2d}	$\overline{O}_{1d}, \overline{O}_{2d}$	
Н	Х	Х	X	Χ	Н	L	Н	L	Н	L	Н	L	
L	L	L	L	L	L	Н	L	Н	L	Н	L	Н	
L	L	L	L	Н	L	Н	L	Н	L	Н	Н	L	
L	L	L	Н	L	L	Н	L	Н	Н	L	L	Н	
L	L	L	Н	Н	L	Н	L	Н	Н	L	Н	L	
L	L	Н	L	L	L	Н	Н	L	L	Н	L	Н	
L	L	Н	L	Н	L	Н	Н	L	L	Н	Н	L	
L	L	Н	Н	L	L	Н	Н	L	Н	L	L	Н	
L	L	Н	Н	Н	L	Н	Н	L	Н	L	Н	L	
L	Н	L	L	L	Н	L	L	Н	L	Н	L	Н	
L	Н	L	L	Н	Н	L	L	Н	L	Н	Н	L	
L	Н	L	Н	L	Н	L	L	Н	Н	L	L	Н	
L	Н	L	Н	Н	Н	L	L	Н	Н	L	Н	L	
L	Н	Н	L	L	Н	L	Н	L	L	Н	L	Н	
L	Н	Н	L	Н	Н	L	Н	L	L	Н	Н	L	
L	Н	Н	Н	L	Н	L	Н	L	Н	L	L	Н	
L	Н	Н	Н	Н	Н	L	Н	L	Н	L	Н	L	

H = HIGH Voltage Level L = LOW Voltage Level X = Don't Care

Absolute Maximum Ratings(Note 1)

Recommended Operating Conditions

Case Temperature (T_C)

 $\begin{array}{ccc} \text{Commercial} & 0^{\circ}\text{C to } +85^{\circ}\text{C} \\ \text{Industrial} & -40^{\circ}\text{C to } +85^{\circ}\text{C} \\ \text{Supply Voltage (V}_{EE}) & -5.7\text{V to } -4.2\text{V} \\ \end{array}$

Note 1: The "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. The device should not be operated at these limits. The parametric values defined in the Electrical Characteristics tables are not guaranteed at the absolute maximum ratings. The "Recommended Operating Conditions" table will define the conditions for actual device operation.

Note 2: ESD testing conforms to MIL-STD-883, Method 3015.

Commercial Version

DC Electrical Characteristics (Note 3)

 $V_{EE} = -4.2 V$ to -5.7 V, $V_{CC} = V_{CCA} = GND$, $T_{C} = 0 ^{\circ} C$ to $+85 ^{\circ} C$

Symbol											
		IVIIII	тур	IVIAX	Ullits						
V _{OH}	Output HIGH Voltage	-1025	-955	-870	mV	V _{IN} =V _{IH} (Max)	Loading with				
V _{OL}	Output LOW Voltage	-1830	-1705	-1620	1111	or V _{IL (Min)}	50Ω to −2.0V				
V _{OHC}	Output HIGH Voltage	-1035			mV	$V_{IN} = V_{IH (Min)}$	Loading with				
V _{OLC}	Output LOW Voltage			-1610	1111	or V _{IL (Max)}	50Ω to –2.0V				
V _{IH}	Input HIGH Voltage	-1165		-870	mV	Guaranteed HIGH Signal					
						for All Inputs					
V _{IL}	Input LOW Voltage	-1830		-1475	mV	Guaranteed LOW Signal					
						for All Inputs					
I _{IL}	Input LOW Current	0.50			μΑ	$V_{IN} = V_{IL (Min)}$					
I _{IH}	Input HIGH Current										
	Data			350	μΑ	V _{IN} = V _{IH (Max)}					
	Enable	э		240							
I _{EE}	Power Supply Current	-59		-29	mA	Inputs OPEN					

Note 3: The specified limits represent the "worst case" value for the parameter. Since these values normally occur at the temperature extremes, additional noise immunity and guardbanding can be achieved by decreasing the allowable system operating ranges. Conditions for testing shown in the tables are chosen to guarantee operation under "worst case" conditions.

DIP AC Electrical Characteristics

 $V_{EE} = -4.2V \text{ to } -5.7V, V_{CC} = V_{CCA} = GND$

Symbol	Parameter	T _C =	$T_C = 0^{\circ}C$		T _C = +25°C		T _C = +85°C		Conditions	
	raiametei	Min	Max	Min	Max	Min	Max	Units	Conditions	
t _{PLH}	Propagation Delay	0.55	1.30	0.55	1.30	0.55	1.40	ns		
t _{PHL}	Data to Output	0.55	1.50	0.55	1.50	0.55	1.40	113	Figures 1, 2	
t _{PLH}	Propagation Delay	0.80	1.80	0.80	1.80	0.80	1.90	no	(Note 4)	
t _{PHL}	Enable to Output	0.60	1.00	0.60	1.00	0.60	1.90	ns		
t _{TLH}	Transition Time	0.45	1.30	0.45	1.30	0.45	1.30	no	Figures 1, 2	
t _{THL}	20% to 80%, 80% to 20%	0.45	1.30	0.45	1.30	0.45	1.30	ns	Figures 1, 2	

Note 4: The propagation delay specified is for single output switching. Delays may vary up to 150 ps with multiple outputs switching.

Commercial Version (Continued) SOIC and PLCC AC Electrical Characteristics

 $\rm V_{EE} = -4.2V$ to $-5.7V,~V_{CC} = V_{CCA} = GND$

Symbol	Parameter	T _C = 0 ° C		T _C = +25°C		T _C = -	+85°C	Units	Conditions
Symbol	Parameter	Min	Max	Min	Max	Min	Max	Uillis	Conditions
t _{PLH}	Propagation Delay	0.55	1.20	0.55	1.20	0.55	1.30	ns	
t _{PHL}	Data to Output	0.00	1.20	0.00	1.20	0.00	1.00	110	Figures 1, 2
t _{PLH}	Propagation Delay	0.80	1.70	0.80	1.70	0.80	1.80	ns	(Note 5)
t _{PHL}	Enable to Output	0.00	1.70	0.00	1.70	0.00	1.00	110	
t _{TLH}	Transition Time	0.45	1.30	0.45	1.30	0.45	1.30	ns	Figures 1, 2
t _{THL}	20% to 80%, 80% to 20%	0.40	1.00	0.40	1.00	0.40	1.00	110	r iguico 1, 2
toshl	Maximum Skew Common Edge								PLCC Only
	Output-to-Output Variation		280		280		280	ps	(Note 6)
	Data to Output Path								
toshl	Maximum Skew Common Edge								PLCC Only
	Output-to-Output Variation		290		290		290	ps	(Note 6)
	Enable to Output Path								
toslh	Maximum Skew Common Edge								PLCC Only
	Output-to-Output Variation		330		330		330	ps	(Note 6)
	Data to Output Path								
t _{OSLH}	Maximum Skew Common Edge								PLCC Only
	Output-to-Output Variation		360		360		360	ps	(Note 6)
	Enable to Output Path								
t _{OST}	Maximum Skew Opposite Edge								PLCC Only
	Output-to-Output Variation		330		330		330	ps	(Note 6)
	Data to Output Path								
t _{OST}	Maximum Skew Opposite Edge								PLCC Only
	Output-to-Output Variation		360		360		360	ps	(Note 6)
	Enable to Output Path								
t _{PS}	Maximum Skew								PLCC Only
	Pin (Signal) Transition Variation		200		200		200	ps	(Note 6)
	Data to Output Path								
t _{PS}	Maximum Skew								PLCC Only
	Pin (Signal) Transition Variation		200		200		200	ps	(Note 6)
	Enable to Output Path								

Note 5: The propagation delay specified is for single output switching. Delays may vary up to 150 ps with multiple outputs switching.

Note 6: Output-to-Output Skew is defined as the absolute value of the difference between the actual propagation delay for any outputs within the same packaged device. The specifications apply to any outputs switching in the same direction either HIGH-to-LOW (toSHL), or LOW-to-HIGH (toSLH), or in opposite directions both HL and LH (toST). Parameters toST and toS

Industrial Version

PLCC DC Electrical Characteristics (Note 7)

 $V_{EE} = -4.2V$ to -5.7V, $V_{CC} = V_{CCA} = GND$, $T_{C} = -40^{\circ}C$ to $+85^{\circ}C$

Symbol	Parameter		$T_C = -40^{\circ}C$		$T_C = 0^{\circ}C \text{ to } +85^{\circ}C$		Units	Conditions		
- Cymbol	i urumeter	Min	Max	Min	Max	00	Conditions			
V _{OH}	Output HIGH Voltage		-1085	-870	-1025	-870	mV	$V_{IN} = V_{IH(Max)}$	Loading with	
V _{OL}	Output LOW Voltage		-1830	-1575	-1830	-1620	1111	or V _{IL(Min)}	50Ω to $-2.0V$	
V _{OHC}	Output HIGH Voltage		-1095		-1035		mV	$V_{IN} = V_{IH(Min)}$	Loading with	
V _{OLC}	Output LOW Voltage			-1565		-1610	1111	or V _{IL(Max)}	50Ω to $-2.0V$	
V _{IH}	Input HIGH Voltage		-1170	-870	-1165	-870	mV	Guaranteed HIGH Signal for All Inputs		
V _{IL}	Input LOW Voltage		-1830	-1480	-1830	-1475	mV	Guaranteed LOW Signal	for All Inputs	
I _{IL}	Input LOW Current		0.50		0.50		μΑ	$V_{IN} = V_{IL(Min)}$		
I _{IH}	Input HIGH Current									
		Data		350		350	μΑ	$V_{IN} = V_{IH(Max)}$		
		Enable		240		240				
I _{EE}	Power Supply Current		-59	-29	-59	-29	mA	Inputs OPEN		

Note 7: The specified limits represent the "worst case" value for the parameter. Since these values normally occur at the temperature extremes, additional noise immunity and guardbanding can be achieved by decreasing the allowable system operating ranges. Conditions for testing shown in the tables are chosen to guarantee operation under "worst case" conditions.


PLCC AC Electrical Characteristics

 $\rm V_{EE} = -4.2V$ to $-5.7V,~V_{CC} = V_{CCA} = GND$

Symbol	Parameter	T _C =	–40°C	T _C = -	+25°C	$T_C = +85^{\circ}C$		Units	Conditions
Cymbol	T arameter	Min	Max	Min	Max	Min	Max	Oilles	Conditions
t _{PLH}	Propagation Delay	0.55	1.20	0.55	1.20	0.55	1.30	ns	
t _{PHL}	Data to Output	0.55	1.20	0.55	1.20	0.55	1.50	113	Figures 1, 2
t _{PLH}	Propagation Delay	0.80	1.70	0.80	1.70	0.80	1.80	ns	(Note 8)
t _{PHL}	Enable to Output	0.00	1.70	0.80	1.70	0.00	1.00	115	
t _{TLH}	Transition Time	0.45	1.30	0.45	1.30	0.45	1.30	ns	Figures 1, 2
t _{THL}	20% to 80%, 80% to 20%	0.43	1.50	0.45	1.50	0.43	1.50	115	rigules 1, 2

Note 8: The propagation delay specified is for single output switching. Delays may vary up to 150 ps with multiple outputs switching.

Test Circuitry



Notes:

 V_{CC} , $V_{CCA} = +2V$, $V_{EE} = -2.5V$.

L1 and L2 = equal length 50Ω impedance lines.

 $R_T = 50\Omega$ terminator internal to scope.


Decoupling 0.1 μF from GND to V_{CC} and $\text{V}_{\text{EE}}.$


All unused outputs are loaded with 50Ω to GND.

 $C_L = \text{Fixture and stray capacitance} \leq 3 \text{ pF.}$


FIGURE 1. AC Test Circuit

Switching Waveforms





Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



28-Lead Plastic Lead Chip Carrier (PLCC), JEDEC MO-047, 0.450 Square Package Number V28A

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com