

December 2007

# 74ABT244 Octal Buffer/Line Driver with 3-STATE Outputs

### **Features**

- Non-inverting buffers
- Output sink capability of 64mA, source capability of 32mA
- Guaranteed output skew
- Guaranteed multiple output switching specifications
- Output switching specified for both 50pF and 250pF loads
- Guaranteed simultaneous switching, noise level and dynamic threshold performance
- Guaranteed latchup protection
- High-impedance, glitch-free bus loading during entire power up and power down cycle
- Nondestructive, hot-insertion capability
- Disable time less than enable time to avoid bus contention

## **General Description**

The ABT244 is an octal buffer and line driver with 3-STATE outputs designed to be employed as a memory and address driver, clock driver, or bus-oriented transmitter/receiver.

## **Ordering Information**

Order Number	Package Number	Package Description
74ABT244CSC	M20B	20-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-013, 0.300" Wide
74ABT244CSJ	M20D	20-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
74ABT244CMSA	MSA20	20-Lead Shrink Small Outline Package (SSOP), JEDEC MO-150, 5.3mm Wide
74ABT244CMTC	MTC20	20-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide

Device also available in Tape and Reel. Specify by appending suffix letter "X" to the ordering number.

All packages are lead free per JEDEC: J-STD-020B standard.

## **Connection Diagram**



## **Pin Descriptions**

Pin Names	Description
$\overline{OE}_1, \overline{OE}_2$	Output Enable Input (Active LOW)
I <sub>0</sub> —I <sub>7</sub>	Inputs
O <sub>0</sub> –O <sub>7</sub>	Outputs

## **Truth Table**

OE <sub>1</sub>	I <sub>0–3</sub>	O <sub>0-3</sub>	$\overline{OE}_2$	I <sub>4-7</sub>	O <sub>4-7</sub>
Н	Х	Z	Н	Х	Z
L	Н	Н	L	Н	Н
L	L	L	L	L	L

H = HIGH Voltage Level

L = LOW Voltage Level

X = Immaterial

Z = High Impedance

## **Absolute Maximum Ratings**

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only.

Symbol	Parameter	Rating
T <sub>STG</sub>	Storage Temperature	–65°C to +150°C
T <sub>A</sub>	Ambient Temperature Under Bias	–55°C to +125°C
TJ	Junction Temperature Under Bias	–55°C to +150°C
V <sub>CC</sub>	V <sub>CC</sub> Pin Potential to Ground Pin	-0.5V to +7.0V
V <sub>IN</sub>	Input Voltage <sup>(1)</sup>	-0.5V to +7.0V
I <sub>IN</sub>	Input Current <sup>(1)</sup>	-30mA to +5.0mA
Vo	Voltage Applied to Any Output	
	Disabled or Power-Off State	–0.5V to 5.5V
	HIGH State	–0.5V to $V_{CC}$
	Current Applied to Output in LOW State (Max.)	twice the rated I <sub>OL</sub> (mA)
	DC Latchup Source Current	–500mA
	Over Voltage Latchup (I/O)	10V

### Note:

1. Either voltage limit or current limit is sufficient to protect inputs.

## **Recommended Operating Conditions**

The Recommended Operating Conditions table defines the conditions for actual device operation. Recommended operating conditions are specified to ensure optimal performance to the datasheet specifications. Fairchild does not recommend exceeding them or designing to absolute maximum ratings.

Symbol	Parameter	Rating
T <sub>A</sub>	Free Air Ambient Temperature	–40°C to +85°C
V <sub>CC</sub>	Supply Voltage	+4.5V to +5.5V
$\Delta V / \Delta t$	Minimum Input Edge Rate	
	Data Input	50mV/ns
	Enable Input	20mV/ns

Symbol	P	arameter	V <sub>CC</sub>	Conditions	Min.	Тур.	Max.	Units
V <sub>IH</sub>	Input HIGH	Voltage		Recognized HIGH Signal	2.0			V
V <sub>IL</sub>	Input LOW	Voltage		Recognized LOW Signal			0.8	V
V <sub>CD</sub>	Input Clam	p Diode Voltage	Min.	$I_{IN} = -18 \text{mA}$			-1.2	V
V <sub>OH</sub>	Output HIG	H Voltage	Min.	$I_{OH} = -3mA$	2.5			V
				$I_{OH} = -32mA$	2.0			
V <sub>OL</sub>	Output LOV	V Voltage		I <sub>OL</sub> = 64mA			0.55	V
I <sub>IH</sub>	Input HIGH	Current	Max.	$V_{IN} = 2.7V^{(3)}$			1	μA
				$V_{IN} = V_{CC}$			1	
I <sub>BVI</sub>	Input HIGH Breakdown		Max.	$V_{IN} = 7.0V$			7	μA
IIL	Input LOW Current	Max.	$V_{IN} = 0.5V^{(3)}$			-1	μA	
				$V_{IN} = 0.0V$			-1	
V <sub>ID</sub>	Input Leakage Test		0.0	I <sub>ID</sub> = 1.9μA, All Other Pins Grounded	4.75			V
I <sub>OZH</sub>	Output Leakage Current		0-5.5V	$V_{OUT} = 2.7V, \overline{OE}_n = 2.0V$			10	μA
I <sub>OZL</sub>	Output Lea	kage Current	0-5.5V	$V_{OUT} = 0.5V, \overline{OE}_n = 2.0V$			-10	μA
I <sub>OS</sub>	Output Sho	rt-Circuit Current	Max.	$V_{OUT} = 0.0V$	-100		-275	mA
I <sub>CEX</sub>	Output High	h Leakage Current	Max.	$V_{OUT} = V_{CC}$			50	μA
I <sub>ZZ</sub>	Bus Draina	ge Test	0.0	V <sub>OUT</sub> = 5.5V, All Others GND			100	μA
I <sub>CCH</sub>	Power Sup	oly Current	Max.	All Outputs HIGH			50	μA
I <sub>CCL</sub>	Power Sup	oly Current	Max.	All Outputs LOW			30	mA
I <sub>CCZ</sub>	Power Sup	oly Current	Max.	$\overline{OE}_n = V_{CC}$ , All Others at $V_{CC}$ or Ground			50	μA
I <sub>CCT</sub>	Additional	Outputs Enabled	Max.	$V_{I} = V_{CC} - 2.1V$			2.5	mA
	I <sub>CC</sub> /Input	Outputs 3-STATE		Enable Input $V_I = V_{CC} - 2.1V$			2.5	mA
		Outputs 3-STATE		Data Input $V_I = V_{CC} - 2.1V$ , All Others at $V_{CC}$ or Ground			50	μA
ICCD	Dynamic I <sub>CC</sub> No Load <sup>(3)</sup>		Max.	Outputs OPEN, $\overline{OE}_n = GND^{(2)}$ , One-Bit Toggling, 50% Duty Cycle			0.1	mA/ MHz

### Notes:

2. For 8-bit toggling,  $I_{CCD} < 0.8 \text{mA/MHz}.$ 

3. Guaranteed, but not tested.

## **DC Electrical Characteristics**

SOIC package.

			Conditions C <sub>L</sub> = 50pF,				
Symbol	Parameter	V <sub>CC</sub>	$R_L = 500\Omega$	Min.	Тур.	Max.	Units
V <sub>OLP</sub>	Quiet Output Maximum Dynamic V <sub>OL</sub>	5.0	$T_A = 25^{\circ}C^{(4)}$		0.5	0.8	V
V <sub>OLV</sub>	Quiet Output Minimum Dynamic V <sub>OL</sub>	5.0	$T_A = 25^{\circ}C^{(4)}$	-1.3	-0.8		V
V <sub>OHV</sub>	Minimum HIGH Level Dynamic Output Voltage	5.0	$T_A = 25^{\circ}C^{(6)}$	2.7	3.1		V
V <sub>IHD</sub>	Minimum HIGH Level Dynamic Input Voltage	5.0	$T_A = 25^{\circ}C^{(5)}$	2.0	1.5		V
V <sub>ILD</sub>	Maximum LOW Level Dynamic Input Voltage	5.0	$T_A = 25^{\circ}C^{(5)}$		1.1	0.8	V

### Notes:

4. Max number of outputs defined as (n). n − 1 data inputs are driven 0V to 3V. One output at LOW. Guaranteed, but not tested.

5. Max number of data inputs (n) switching. n – 1 inputs switching 0V to 3V. Input-under-test switching: 3V to threshold (V<sub>ILD</sub>), 0V to threshold (V<sub>IHD</sub>). Guaranteed, but not tested.

6. Max number of outputs defined as (n). n – 1 data inputs are driven 0V to 3V. One output HIGH. Guaranteed, but not tested.

## **AC Electrical Characteristics**

SOIC and SSOP package.

		$\begin{array}{c} T_{A} = +25^{\circ}C, \\ V_{CC} = +5V, \\ C_{L} = 50 pF \end{array}$				$\label{eq:T_A} \begin{array}{ c c c } T_A = -40^{\circ} C \ to \ +85^{\circ} C, \\ V_{CC} = \ 4.5 V - 5.5 V, \\ C_L = \ 50 p F \end{array}$			
Symbol	Parameter	Min.	Тур.	Max.	Min.	Max.	Min.	Max.	Units
t <sub>PLH</sub>	Propagation Delay	1.0	2.5	3.6	1.0	5.3	1.0	3.6	ns
t <sub>PHL</sub>	Data to Outputs	1.0	2.3	3.6	1.0	5.0	1.0	3.6	
t <sub>PZH</sub>	Output Enable Time	1.5	3.5	6.0	0.8	6.5	1.5	6.0	ns
t <sub>PZL</sub>		1.5	3.6	6.0	1.2	7.9	1.5	6.0	
t <sub>PHZ</sub>	Output Disable Time	1.7	3.5	5.6	1.2	7.6	1.7	5.6	ns
t <sub>PLZ</sub>		1.7	3.3	5.6	1.0	7.9	1.7	5.6	

## **Extended AC Electrical Characteristics**

SOIC package.

		$\label{eq:tau} \begin{array}{l} T_A - 40^\circ C \ to \ +85^\circ C, \\ V_{CC} = 4.5 V - 5.5 V, \\ C_L = 50 p F, \\ 8 \ Outputs \\ Switching^{(7)} \end{array}$		$\begin{split} T_{A} &= -40^{\circ}\text{C to } +85^{\circ}\text{C}, \\ V_{CC} &= 4.5\text{V} -5.5\text{V}, \\ C_{L} &= 250\text{pF}, \\ 1 \text{ Output} \\ \text{Switching}^{(8)} \end{split}$		$\label{eq:TA} \begin{array}{l} T_A = -40^\circ \text{C to } +85^\circ \text{C}, \\ V_{CC} = 4.5 \text{V} -5.5 \text{V}, \\ C_L = 250 \text{pF}, \\ 8 \text{ Outputs} \\ \text{Switching}^{(9)} \end{array}$			
Symbol	Parameter	Min.	Тур.	Max.	Min.	Max.	Min.	Max.	Units
f <sub>TOGGLE</sub>	Max Toggle Frequency		100						MHz
t <sub>PLH</sub>	Propagation Delay,	1.5		5.0	1.5	6.0	2.5	8.5	ns
t <sub>PHL</sub>	Data to Outputs	1.5		5.0	1.5	6.0	2.5	8.5	
t <sub>PZH</sub>	Output Enable Time	1.5		6.5	2.5	7.5	2.5	10.0	ns
t <sub>PZL</sub>		1.5		6.5	2.5	7.5	2.5	12.0	
t <sub>PHZ</sub>	Output Disable Time	1.0		5.6		(10)	(*	10)	ns
t <sub>PLZ</sub>		1.0		5.6					

### Notes:

7. This specification is guaranteed but not tested. The limits apply to propagation delays for all paths described switching in phase (i.e., all LOW-to-HIGH, HIGH-to-LOW, etc.).

- This specification is guaranteed but not tested. The limits represent propagation delay with 250pF load capacitors in place of the 50pF load capacitors in the standard AC load. This specification pertains to single output switching only.
- 9. This specification is guaranteed but not tested. The limits represent propagation delays for all paths described switching in phase (i.e., all LOW-to-HIGH, HIGH-to-LOW, etc.) with 250pF load capacitors in place of the 50pF load capacitors in the standard AC load.
- 10. The 3-STATE delays are dominated by the RC network (500Ω, 250pF) on the output and have been excluded from the datasheet.

### Skew

		$T_{A} = -40^{\circ}C \text{ to } +85^{\circ}C,$ $V_{CC} = 4.5V - 5.5V,$ $C_{L} = 50\text{pF},$ 8 Outputs Switching <sup>(13)</sup>	$T_A = -40^{\circ}C \text{ to } +85^{\circ}C,$ $V_{CC} = 4.5V-5.5V,$ $C_L = 250\text{pF},$ 8 Outputs Switching <sup>(14)</sup>	
Symbol	Parameter	Max.	Max.	Units
t <sub>OSHL</sub> <sup>(11)</sup>	Pin to Pin Skew, HL Transitions	0.8	1.8	ns
t <sub>OSLH</sub> <sup>(11)</sup>	Pin to Pin Skew, LH Transitions	0.8	1.8	ns
t <sub>PS</sub> <sup>(15)</sup>	Duty Cycle, LH–HL Skew	1.0	2.5	ns
t <sub>OST</sub> <sup>(11)</sup>	Pin to Pin Skew, LH/HL Transitions	1.0	2.5	ns
t <sub>PV</sub> <sup>(12)</sup>	Device to Device Skew, LH/HL Transitions	1.5	3.0	ns

### Notes:

- 11. Skew is defined as the absolute value of the difference between the actual propagation delays for any two separate outputs of the same device. The specification applies to any outputs switching HIGH-to-LOW (t<sub>OSHL</sub>), LOW-to-HIGH (t<sub>OSLH</sub>), or any combination switching LOW-to-HIGH and/or HIGH-to-LOW (t<sub>OST</sub>). The specification is guaranteed but not tested.
- 12. Propagation delay variation for a given set of conditions (i.e., temperature and V<sub>CC</sub>) from device to device. This specification is guaranteed but not tested.
- 13. This specification is guaranteed but not tested. The limits apply to propagation delays for all paths described switching in phase (i.e., all LOW-to-HIGH, HIGH-to-LOW, etc.)
- 14. These specifications guaranteed but not tested. The limits represent propagation delays with 250pF load capacitors in place of the 50pF load capacitors in the standard AC load.
- 15. This describes the difference between the delay of the LOW-to-HIGH and the HIGH-to-LOW transition on the same pin. It is measured across all the outputs (drivers) on the same chip, the worst (largest delta) number is the guaranteed specification. This specification is guaranteed but not tested.

## Capacitance

Symbol	Parameter	Conditions T <sub>A</sub> = 25°C	Тур.	Units
C <sub>IN</sub>	Input Capacitance	$V_{CC} = 0V$	5.0	pF
C <sub>OUT</sub> <sup>(16)</sup>	Output Capacitance	$V_{CC} = 5.0V$	9.0	pF

Note:

16. C<sub>OUT</sub> is measured at frequency f = 1MHz, per MIL-STD-883, Method 3012.



\*Includes jig and probe capacitance

Figure 1. Standard AC Test Load





Figure 2. Test Input Signal Levels

Amplitude	Rep. Rate	t <sub>W</sub>	t <sub>r</sub>	t <sub>f</sub>
3.0V	1 MHz	500ns	2.5ns	2.5ns

**Figure 3. Test Input Signal Requirements** 



Figure 4. Propagation Delay, Pulse Width Waveforms



Figure 5. 3-STATE Output HIGH and LOW Enable and Disable Times



Figure 6. Propagation Delay Waveforms for Inverting and Non-Inverting Functions







### Figure 8. 20-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-013, 0.300" Wide

Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings: http://www.fairchildsemi.com/packaging/





Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings:

http://www.fairchildsemi.com/packaging/



### MTC20REVD1

### Figure 11. 20-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide

Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings:

http://www.fairchildsemi.com/packaging/



SEMICONDUCTOR

### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

ACEx <sup>®</sup> Build it Now <sup>TM</sup> CorePLUS <sup>TM</sup> $CROSSVOLT^{TM}$ CTL <sup>TM</sup> Current Transfer Logic <sup>TM</sup> EcoSPARK <sup>®</sup> EZSWITCH <sup>TM</sup> * $E^{TM}$ Fairchild <sup>®</sup> Fairchild <sup>®</sup> Fairchil	FPS <sup>™</sup> FRFET <sup>®</sup> Global Power Resource <sup>™</sup> Green FPS <sup>™</sup> e-Series <sup>™</sup> GTO <sup>™</sup> <i>i-Lo<sup>™</sup></i> IntelliMAX <sup>™</sup> ISOPLANAR <sup>™</sup> MGgaBuck <sup>™</sup> MICROCOUPLER <sup>™</sup> MicroFET <sup>™</sup> MicroFET <sup>™</sup> MicroFeX <sup>™</sup> MillerDrive <sup>™</sup> Motion-SPM <sup>™</sup> OPTOLOGIC <sup>®</sup> OPTOPLANAR <sup>®</sup>	PDP-SPM <sup>™</sup> Power220 <sup>®</sup> Power247 <sup>®</sup> POWEREDGE <sup>®</sup> Power-SPM <sup>™</sup> PowerTrench <sup>®</sup> Programmable Active Droop <sup>™</sup> QFET <sup>®</sup> QS <sup>™</sup> QT Optoelectronics <sup>™</sup> Quiet Series <sup>™</sup> RapidConfigure <sup>™</sup> SMART START <sup>™</sup> SPM <sup>®</sup> STEALTH <sup>™</sup> SuperFET <sup>™</sup> SuperFET <sup>™</sup> SuperSOT <sup>™</sup> -6 SuperSOT <sup>™</sup> -8	SyncFET <sup>™</sup> Figer Power Franchise <sup>®</sup> The Power Franchise <sup>®</sup> TinyBoost <sup>™</sup> TinyBoost <sup>™</sup> TinyBuck <sup>™</sup> TinyLogic <sup>®</sup> TINYOPTO <sup>™</sup> TinyPOWer <sup>™</sup> TinyPWM <sup>™</sup> TinyWire <sup>™</sup> µSerDes <sup>™</sup> UHC <sup>®</sup> Ultra FRFET <sup>™</sup> UniFET <sup>™</sup> VCX <sup>™</sup>
---	---	---	--

\* EZSWITCH™ and FlashWriter<sup>®</sup> are trademarks of System General Corporation, used under license by Fairchild Semiconductor.

### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Datasheet Identification	Product Status	Definition	
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.	
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improv the design.	
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild Semiconductor. The datasheet is printed for reference information only.	

### PRODUCT STATUS DEFINITIONS