INTEGRATED CIRCUITS



Product specification IC24 Data Handbook 1998 Jun 30

PHILIPS

74ALVT16344

FEATURES

- Multiple V_{CC} and GND pins minimize switching noise
- 5V I/O Compatible
- Live insertion/extraction permitted
- 3-State output buffers
- Power-up 3-State
- Output capability: +64mA/-32mA
- Latch-up protection exceeds 500mA per Jedec JC40.2 Std 17
- ESD protection exceeds 2000 V per MIL STD 883 Method 3015 and 200 V per Machine Model

DESCRIPTION

The 74ALVT16344 high-performance BiCMOS device combines low static and dynamic power dissipation with high speed and high output drive. It is designed for V_{CC} operation at 2.5V or 3.3V with I/O compatibility to 5V.

The 74ALVT16344 is a 1-to-4 address driver used in applications where four separate memory locations must be addressed by a single address.

QUICK REFERENCE DATA

| SYMBOL | PARAMETER | CONDITIONS | TYPI | UNIT | |
|--------------------------------------|---|-----------------------------------|------------|------------|------|
| STMBOL | | T _{amb} = 25℃ | 2.5V | 3.3V | UNIT |
| t _{PLH} t _{PHL} | Propagation delay nAx to nBx or nBx to nAx | C _L = 50pF | 2.5 1.9 | 1.9 1.6 | ns |
| C _{IN} | Input capacitance DIR, OE | $V_I = 0V \text{ or } V_{CC}$ | 3 | 3 | pF |
| C _{Out} Output capacitance | | $V_{I/O} = 0V \text{ or } V_{CC}$ | 9 | 9 | pF |
| I _{CCZ} | Total supply current | Outputs disabled | 40 | 70 | μΑ |

ORDERING INFORMATION

| PACKAGES | TEMPERATURE RANGE | OUTSIDE NORTH AMERICA | NORTH AMERICA | DWG NUMBER |
|------------------------------|-------------------|-----------------------|---------------|------------|
| 56-Pin Plastic SSOP Type III | –40°C to +85°C | 74ALVT16344 DL | AV16344 DL | SOT371-1 |
| 56-Pin Plastic TSSOP Type II | –40°C to +85°C | 74ALVT16344 DGG | AV16344 DGG | SOT364-1 |

PIN DESCRIPTION

| PIN NUMBER | SYMBOL | FUNCTION |
|---|---|-----------------------------------|
| 8, 14, 15, 21, 36, 42, 43, 49 | nA | Data inputs |
| 2, 3, 5, 6, 9, 10, 12, 13, 16, 17, 19, 20, 23, 24, 26, 27, 30,31, 33, 34, 37, 38, 40, 44, 45, 47, 48, 51, 52, 54, 55, | 3, 34, 37, 38, 40, 44, 45, nY _X Data outputs | |
| 1, 28, 29, 56 | ŌĒ | Output enable inputs (active-Low) |
| 4, 11, 18, 25, 32, 39, 46, 53 | GND | Ground (0V) |
| 7, 22, 35, 50 | V _{CC} | Positive supply voltage |

74ALVT16344

| OE1 | 1 | | 56 | OE4 |
|-----------------|----|-----|----|-----------------|
| 1Y0 | 2 | | 55 | 8Y0 |
| 1Y1 | 3 | | 54 | 8Y1 |
| GND | 4 | | 53 | GND |
| 1Y2 | 5 | | 52 | 8Y2 |
| 1Y3 | 6 | | 51 | 8Y3 |
| V _{CC} | 7 | | 50 | V _{CC} |
| 1A | 8 | | 49 | 8A |
| 2Y0 | 9 | | 48 | 7Y0 |
| 2Y1 | 10 | | 47 | 7Y1 |
| GND | 11 | | 46 | GND |
| 2Y2 | 12 | | 45 | 7Y2 |
| 2Y3 | 13 | | 44 | 7Y3 |
| 2A | 14 | | 43 | 7A |
| ЗА | 15 | | 42 | 6A |
| 3Y0 | 16 | | 41 | 6Y0 |
| 3Y1 | 17 | | 40 | 6Y1 |
| GND | 18 | | 39 | GND |
| 3Y2 | 19 | | 38 | 6Y2 |
| 3Y3 | 20 | | 37 | 6Y3 |
| 4A | 21 | | 36 | 5A |
| V _{CC} | 22 | | 35 | V _{CC} |
| 4Y0 | 23 | | 34 | 5Y0 |
| 4Y1 | 24 | | 33 | 5Y1 |
| GND | 25 | | 32 | GND |
| 4Y2 | 26 | | 31 | 5Y2 |
| 4Y3 | 27 | 1 1 | 30 | 5Y3 |
| OE2 | 28 | | 29 | OE3 |
| | | | | |
| | | | SV | 01735 |

PIN CONFIGURATION

FUNCTION TABLE

| INPL | JTS | OUTPUTS | OPERATING MODE | |
|------|-----|---------|----------------|--|
| OE | nA | nYx | | |
| L | L | L | Transparent | |
| L | Н | Н | Transparent | |
| Н | Х | Z | High impedance | |

X = Don't care Z = High impedance "off" state H = High voltage level

L = Low voltage level

LOGIC SYMBOL



74ALVT16344

LOGIC DIAGRAM



74ALVT16344

ABSOLUTE MAXIMUM RATINGS^{1, 2}

| SYMBOL | PARAMETER | CONDITIONS | RATING | UNIT |
|------------------|--------------------------------|-----------------------------|--------------|------|
| V _{CC} | DC supply voltage | | -0.5 to +4.6 | V |
| I _{IK} | DC input diode current | V ₁ < 0 | -50 | mA |
| VI | DC input voltage ³ | | -0.5 to +7.0 | V |
| I _{OK} | DC output diode current | V _O < 0 | -50 | mA |
| V _{OUT} | DC output voltage ³ | Output in Off or High state | -0.5 to +7.0 | V |
| 1 | | Output in Low state | 128 | mA |
| OUT | DC output current | Output in High state | -64 | |
| T _{stq} | Storage temperature range | | -65 to +150 | °C |

NOTES:

 Stresses beyond those listed may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

 The performance capability of a high-performance integrated circuit in conjunction with its thermal environment can create junction temperatures which are detrimental to reliability. The maximum junction temperature of this integrated circuit should not exceed 150°C.

3. The input and output negative voltage ratings may be exceeded if the input and output clamp current ratings are observed.

RECOMMENDED OPERATING CONDITIONS

| SYMBOL | PARAMETER | 2.5V RAN | GE LIMITS | 3.3V RANGE LIMITS | | UNIT |
|------------------|---|----------|-----------|-------------------|-----|------|
| STMBOL | FARAMETER | | MAX | MIN | MAX | UNIT |
| V _{CC} | DC supply voltage | 2.3 | 2.7 | 3.0 | 3.6 | V |
| VI | Input voltage | 0 | 5.5 | 0 | 5.5 | V |
| V _{IH} | V _{IH} High-level input voltage | | | 2.0 | | V |
| V _{IL} | Input voltage | | 0.7 | | 0.8 | V |
| I _{OH} | High-level output current | | -8 | | -32 | mA |
| le. | Low-level output current | | 8 | | 32 | mA |
| IOL | Low-level output current; current duty cycle \leq 50%; f \geq 1kHz | | 24 | | 64 | ШA |
| Δt/Δv | $\Delta t / \Delta v$ Input transition rise or fall rate; Outputs enabled | | 10 | | 10 | ns/V |
| T _{amb} | Operating free-air temperature range | -40 | +85 | -40 | +85 | °C |

74ALVT16344

DC ELECTRICAL CHARACTERISTICS (3.3V ± 0.3V RANGE)

| | | | | | LIMITS | | |
|--------------------|--|---|--------------------------------------|----------------------|------------------|-------|------|
| SYMBOL | PARAMETER | TEST CONDITIONS | | Temp = · | -40°C to | +85°C | UNIT |
| | | | | MIN | TYP ¹ | MAX | |
| V _{IK} | Input clamp voltage | $V_{CC} = 3.0V; I_{IK} = -18mA$ | | | -0.85 | -1.2 | V |
| M | High-level output voltage | $V_{CC} = 3.0$ to 3.6V; $I_{OH} = -100\mu A$ | | V _{CC} -0.2 | V _{CC} | | |
| V _{OH} | l lightevel output voltage | $V_{CC} = 3.0V; I_{OH} = -32mA$ | | 2.0 | 2.3 | | 1 |
| | | V _{CC} = 3.0V; I _{OL} = 100µA | | | 0.07 | 0.2 | |
| V _{OL} | Low-level output voltage | V _{CC} = 3.0V; I _{OL} = 16mA | | | 0.25 | 0.4 | V |
| | | V _{CC} = 3.0V; I _{OL} = 32mA | | | 0.3 | 0.5 | 1 |
| | | V _{CC} = 3.0V; I _{OL} = 64mA | | | 0.4 | 0.55 | 1 |
| | | $V_{CC} = 3.6V; V_I = V_{CC} \text{ or } GND$ | Control ning | | 0.1 | ±1 | |
| | Input leakage current | V _{CC} = 0 or 3.6V; V _I = 5.5V | Control pins | | 0.1 | 10 | |
| I _I | | $V_{CC} = 3.6V; V_{I} = 5.5V$ | | | 0.1 | 10 | μA |
| | | $V_{CC} = 3.6V; V_I = V_{CC}$ | Data pins ⁴ | | 0.1 | 1 | |
| | | $V_{CC} = 3.6V; V_{I} = 0$ | | | 0.1 | -5 | |
| I _{OFF} | Off current | $V_{CC} = 0V; V_{I} \text{ or } V_{O} = 0 \text{ to } 4.5V$ | | | 0.1 | ±100 | μA |
| | Bus Hold current | $V_{CC} = 3V; V_{I} = 0.8V$ | | 75 | 130 | | μA |
| I _{HOLD} | | $V_{CC} = 3V; V_I = 2.0V$ | | -75 | -200 | | μA |
| | A or B outputs | $V_{\rm I} = 0V$ to 3.6V; $V_{\rm CC} = 3.6V^6$ | | ±500 | | | μA |
| I_{EX} | Current into an output in the High state when $V_O > V_{CC}$ | V _O = 5.5V; V _{CC} = 3.0V | | | 10 | 125 | μA |
| I _{PU/PD} | Power up/down 3-State output current ³ | $V_{CC} \le 1.2$ V; $V_O = 0.5$ V to V_{CC} ; $V_I = GND OE/OE = Don't care$ |) or V _{CC} ; | | 1 | ±100 | μA |
| I _{OZH} | 3-State output High current | $V_{CC} = 3.6V; V_{O} = 3.0V; V_{I} = V_{IL} \text{ or } V_{IH}$ | | | 0.5 | 5 | μA |
| I _{OZL} | 3-State output Low current | $V_{CC} = 3.6V; V_{O} = 0.5V; V_{I} = V_{IL} \text{ or } V_{IH}$ | | | 0.5 | -5 | μA |
| ICCH | | V_{CC} = 3.6V; Outputs High, V_{I} = GND or V | V _{CC} , I _{O =} 0 | | 0.06 | 0.1 | |
| I _{CCL} | Quiescent supply current | V_{CC} = 3.6V; Outputs Low, V_{I} = GND or V | $V_{\rm CC, I_{\rm O}=0}$ | | 7 | 8.5 | mA |
| I _{CCZ} | 1 | V _{CC} = 3.6V; Outputs Disabled; V _I = GND |) or V_{CC} , $I_{O} = 0^5$ | | 0.06 | 0.1 | 1 |
| ΔI_{CC} | Additional supply current per input pin ² | $V_{CC} = 3V$ to 3.6V; One input at V_{CC} -0.6° Other inputs at V_{CC} or GND | V, | | 0.05 | 0.4 | mA |

NOTES:

All typical values are at V_{CC} = 3.3V and T_{amb} = 25°C.
This is the increase in supply current for each input at the specified voltage level other than V_{CC} or GND
This parameter is valid for any V_{CC} between 0V and 1.2V with a transition time of up to 10msec. From V_{CC} = 1.2V to V_{CC} = 3.3V ± 0.3V a transition time of 100µsec is permitted. This parameter is valid for T_{amb} = 25°C only.

Unused pins at V_{CC} or GND. 4.

I_{CCZ} is measured with outputs pulled up to V_{CC} or pulled down to ground.
This is the bus hold overdrive current required to force the input to the opposite state.

AC CHARACTERISTICS (3.3V ± 0.3V RANGE)

GND = 0V, $t_R = t_F = 2.5ns$, $C_L = 50pF$, $R_L = 500\Omega$

| | | | | LIMITS | | |
|--------------------------------------|--|----------|--|------------|------------|----|
| SYMBOL | PARAMETER | WAVEFORM | T _{amb} = -40 to +85°C V _{CC} = +3.3V ±0.3V | | UNIT | |
| | | | MIN | TYP | MAX | |
| t _{PLH} t _{PHL} | Propagation delay nAx to nYx | 1 | 0.5 0.5 | 1.9 1.6 | 3.0 2.5 | ns |
| t _{PZH} t _{PZL} | Output enable time to High and Low level | 2 | 1.0 1.0 | 2.8 2.3 | 4.7 3.6 | ns |
| t _{PHZ} t _{PLZ} | Output disable time from High and Low level | 2 | 1.0 1.0 | 3.7 2.3 | 5.5 4.1 | ns |

74ALVT16344

DC ELECTRICAL CHARACTERISTICS (2.5V \pm 0.2V RANGE)

| | | | | LIMITS | | | |
|---------------------|--|--|-----------------------------|----------------------|------------------|-------|----|
| SYMBOL | PARAMETER | TEST CONDITIONS | | Temp = | -40°C to | +85°C | |
| | | | | MIN | TYP ¹ | MAX | |
| V _{IK} | Input clamp voltage | $V_{CC} = 2.3V; I_{IK} = -18mA$ | | | -0.85 | -1.2 | V |
| V _{OH} | High-level output voltage | $V_{CC} = 2.3$ to 2.7V; $I_{OH} = -100\mu A$ | | V _{CC} -0.2 | V _{CC} | | v |
| VОН | nigh-level output voltage | $V_{CC} = 2.3V; I_{OH} = -8mA$ | | 1.7 | 2.1 | | v |
| Vol | Low-level output voltage | $V_{CC} = 2.3V; I_{OL} = 100\mu A$ | | | 0.07 | 0.2 | v |
| VOL | Low-level output voltage | $V_{CC} = 2.3V; I_{OL} = 24mA$ | | | 0.3 | 0.5 | v |
| | | $V_{CC} = 2.7V$; $V_I = V_{CC}$ or GND | Control pins | | 0.1 | ±1 | |
| | | $V_{CC} = 0 \text{ or } 2.7 \text{V}; \text{ V}_{\text{I}} = 5.5 \text{V}$ | Control pins | | 0.1 | 10 | |
| I _I | Input leakage current | $V_{CC} = 2.7V; V_{I} = 5.5V$ | | | 0.1 | 10 | μA |
| | | $V_{CC} = 2.7V; V_{I} = V_{CC}$ | Data pins ⁴ | | 0.1 | 1 | |
| | | $V_{CC} = 2.7V; V_I = 0$ | 1 | | 0.1 | -5 | |
| I _{OFF} | Off current | $V_{CC} = 0V$; V_{I} or $V_{O} = 0$ to 4.5V | | | 0.1 | ±100 | μA |
| I _{HOLD} 6 | Bus Hold current | $V_{CC} = 2.5V; V_{I} = 0.8V$ | | | 105 | | μA |
| | A inputs | $V_{CC} = 2.5V; V_I = 2.0V$ | | | 10 | | μΑ |
| I_{EX} | Current into an output in the High state when $V_O > V_{CC}$ | V _O = 5.5V; V _{CC} = 2.3V | | | 10 | 125 | μA |
| I _{PU/PD} | Power up/down 3-State output current ³ | $V_{CC} \le 1.2$ V; $V_O = 0.5$ V to V_{CC} ; $V_I = GNE OE/OE = Don't care$ | D or V _{CC} | | 1 | 100 | μA |
| I _{OZH} | 3-State output High current | V_{CC} = 2.7V; V_{O} = 2.3V; V_{I} = V_{IL} or V_{IH} | | | 0.5 | 5 | μA |
| I _{OZL} | 3-State output Low current | V_{CC} = 2.7V; V_{O} = 0.5V; V_{I} = V_{IL} or V_{IH} | | | 0.5 | -5 | μA |
| I _{CCH} | | $V_{CC} = 2.7V$; Outputs High, $V_I = GND$ or | V_{CC} , $I_{O} = 0$ | | 0.04 | 0.1 | |
| I _{CCL} | Quiescent supply current | $V_{CC} = 2.7V$; Outputs Low, $V_I = GND$ or V_I | $I_{\rm CC, I_{\rm O} = 0}$ | | 5.0 | 6.5 | mA |
| I _{CCZ} |] | V_{CC} = 2.7V; Outputs Disabled; V_I = GND | 0 or $V_{CC, I_{O}} = 0^5$ | | 0.04 | 0.1 | |
| ΔI_{CC} | Additional supply current per input pin ² | V_{CC} = 2.3V to 2.7V; One input at $V_{CC}\text{0}$ Other inputs at V_{CC} or GND | .6V, | | 0.04 | 0.4 | mA |

NOTES:

All typical values are at V_{CC} = 2.5V and T_{amb} = 25°C.
This is the increase in supply current for each input at the specified voltage level other than V_{CC} or GND
This parameter is valid for any V_{CC} between 0V and 1.2V with a transition time of up to 10msec. From V_{CC} = 1.2V to V_{CC} = 2.5V ± 0.2V a transition time of 100µsec is permitted. This parameter is valid for T_{amb} = 25°C only.
Unused pins at V_{CC} or GND.
I_{CCZ} is measured with outputs pulled up to V_{CC} or pulled down to ground.
Not guaranteed.

AC CHARACTERISTICS (2.5V \pm 0.2V RANGE) GND = 0V, t_R = t_F = 2.5ns, C_L = 50pF, R_L = 500 Ω

| | | | | LIMITS | | |
|--------------------------------------|--|----------|--|------------|------------|----|
| SYMBOL | PARAMETER | WAVEFORM | T _{amb} = -40 to +85°C V _{CC} = +2.5V ±0.2V | | UNIT | |
| | | | MIN | TYP | MAX | |
| t _{PLH} t _{PHL} | Propagation delay nAx to nYx | 1 | 0.5 0.5 | 2.5 1.9 | 4.2 3.9 | ns |
| t _{PZH} t _{PZL} | Output enable time to High and Low level | 2 | 1.0 1.0 | 3.5 2.8 | 6.1 4.6 | ns |
| t _{PHZ} t _{PLZ} | Output disable time from High and Low level | 2 | 1.0 1.0 | 2.8 3.1 | 5.3 4.9 | ns |

74ALVT16344

AC WAVEFORMS

 $\begin{array}{l} V_{M} = 1.5V \mbox{ for } V_{CC} \geq 3.0V; \mbox{ } V_{M} = V_{CC}/2 \mbox{ for } V_{CC} \leq 2.7V \\ V_{X} = V_{OL} + 0.3V \mbox{ for } V_{CC} \geq 3.0V; \mbox{ } V_{X} = V_{OL} + 0.15V \mbox{ for } V_{CC} \leq 2.7V \\ V_{Y} = V_{OH} - 0.3V \mbox{ for } V_{CC} \geq 3.0V; \mbox{ } V_{Y} = V_{OH} - 0.15V \mbox{ for } V_{CC} \leq 2.7V \\ \end{array}$



Waveform 1. Input (nAx) to Output (nYx) Propagation Delays



Waveform 2. 3-State Output Enable and Disable Times

TEST CIRCUIT AND WAVEFORM



SW00205

74ALVT16344



| OUTLINE | | REFERENCES | | | EUROPEAN | ISSUE DATE |
|----------|-----|------------|------|--|------------|----------------------------------|
| VERSION | IEC | JEDEC | EIAJ | | PROJECTION | 1550E DATE |
| SOT371-1 | | MO-118AB | | | | -93-11-02 95-02-04 |

74ALVT16344



74ALVT16344

NOTES

74ALVT16344

Data sheet status

| Data sheet status | Product status | Definition [1] |
|---------------------------|-------------------|---|
| Objective specification | Development | This data sheet contains the design target or goal specifications for product development. Specification may change in any manner without notice. |
| Preliminary specification | Qualification | This data sheet contains preliminary data, and supplementary data will be published at a later date. Philips Semiconductors reserves the right to make chages at any time without notice in order to improve design and supply the best possible product. |
| Product specification | Production | This data sheet contains final specifications. Philips Semiconductors reserves the right to make changes at any time without notice in order to improve design and supply the best possible product. |

[1] Please consult the most recently issued datasheet before initiating or completing a design.

Definitions

Short-form specification — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

Limiting values definition - Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

Application information - Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Disclaimers

Life support — These products are not designed for use in life support appliances, devices or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

Right to make changes — Philips Semiconductors reserves the right to make changes, without notice, in the products, including circuits, standard cells, and/or software, described or contained herein in order to improve design and/or performance. Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no license or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

Philips Semiconductors 811 East Arques Avenue P.O. Box 3409 Sunnyvale, California 94088-3409 Telephone 800-234-7381

© Copyright Philips Electronics North America Corporation 1998 All rights reserved. Printed in U.S.A.

Document order number:

print code

Date of release: 06-98 9397-750-04065

Let's make things better.



PHILIPS