

PRODUCT INFORMATION

Beam Pentode

Page 1 12-72

36LW6

FOR TV HORIZONTAL-DEFLECTION AMPLIFIER APPLICATIONS

The 36LW6 beam power pentode is designed for horizontal-deflection of 90° and 110° color picture tubes from power supplies of 280 to over 400 volts. It is particularly well suited for feedback scan regulation systems since it provides high peak plate current with high screen voltage and relatively high negative end-of-scan grid drive voltage for great control latitude. The great power handling capability of the 36LW6 results from a new integral fin and radiator anode design that achieves very uniform heat distribution over the entire surface of its larger T-14 bulb. In addition, its low knee voltage minimizes snivets without the necessity of supplying special voltages to the beam plates.

Except for heater characteristics and ratings, the 36LW6 is identical to the 6LW6.

GENERAL

ELECTRICAL

Cathode – Coated Unipotential	
Heater Characteristics and Ratings	
Heater Voltage, AC or DC *	Volts
Heater Current •	Amperes
Heater Warm-up Time, average 🔺 11	Seconds

NOTES

- * Heater voltage for a bogey tube at If= 0.45 Amperes
- The equipment designer should design the equipment so that heater current is centered at the specified bogey value, with heater supply variations restricted to maintain heater current within the specified tolerance.
- ▲ The time required for the voltage across the heater to reach 80 percent of the bogey value after applying 4 times the bogey heater voltage to a circuit consisting of the tube heater in series with a resistance equal to 3 times the bogey heater voltage divided by the bogey heater current.

The tubes and arrangements disclosed herein may be covered by patents of General Electric Company or others. Neither the disclosure of any information herein nor the sale of tubes by General Electric Company conveys any license under patent claims covering combinations of tubes with other devices or elements. In the absence of an express written agreement to the contrary, General Electric Company assumes no liability for patent infringement arising out of any use of the tubes with other devices or elements by any purchaser of tubes or others.

