

# engineering data service



### MECHANICAL DATA

| Dimensions Per Outline                                      |      |
|---|------|
| Mounting Position Any (two gaskets supplied with each tube) |      |
| Ambient temperature range (non-operating)<br>-40 to+100°    | С    |
| Net weight (Approximately) 0.11                             | lbs. |

#### ELECTRICAL DATA

#### **GENERAL DATA**

| Center Frequency | • | • | • |  |  |  | • |  |  |  |  |  |  | • | 9375 | Mc |
|------------------|---|---|---|--|--|--|---|--|--|--|--|--|--|---|------|----|
|------------------|---|---|---|--|--|--|---|--|--|--|--|--|--|---|------|----|

#### **RATINGS** (Absolute)

| Transmitter Peak Power (min.) |  |  |  |   |   | . 4 | KW |
|-------------------------------|--|--|--|---|---|-----|----|
| (m <b>a</b> x.)               |  |  |  | • | • | 500 | KW |

#### TYPICAL OPERATION

| Power Output |  |  |   |  |  |  |   |   | 200        | KW |
|--------------|--|--|---|--|--|--|---|---|------------|----|
| Duty Cycle . |  |  |   |  |  |  | • |   | 0.001      |    |
| 0            |  |  |   |  |  |  |   |   | 1.2 to 1.0 |    |
| Frequency .  |  |  | • |  |  |  | · | • | 9375       | Mc |

#### LOW LEVEL CHARACTERISTICS

| Loaded Q (Center Frequency)                 |  | . 8.0 |
|---|--|-------|
| Tuning Conductance (Center Frequency) G/Yo  |  | . 0.1 |
| Tuning Susceptance (Center Frequency) B/Yo. |  | ±.06  |

#### HIGH LEVEL CHARACTERISTICS

| Arc Loss (max | .) (Note 1)  |   |  |   |  |   | 0.8  | db   |
|---------------|--------------|---|--|---|--|---|------|------|
| High Level VS | SWR (Note 2) | • |  |   |  |   | 1.10 |      |
| Firing Time   | (Note 3)     |   |  | • |  | • | . 10 | sec. |

Note 1: The power loss in the arc shall be less that 680 peak watts.

$$\frac{P}{P-PL} = \frac{4000}{4000-680} = 1.20 \ (0.8 \ db)$$

Note 2:  $P_o = 200 \text{ kw}$ ;  $t_p = 1.0 \text{ } \mu \text{sec}$ ; prr = 1000; 9375 Mc; Load VSWR = 1.03 (max.), VSWR of tube 1.1 to 1.0

Note 3:  $P_0 = 4 \text{ kw}$ ;  $t_p = 0.45$  to 0.65  $\mu$ sec; prr = 1000

## QUICK REFERENCE DATA

The Sylvania Type 5864 is a broadband X-Band ATR gas switching tube designed to decouple effectively the transmitter from a common transmitting and receiving antenna during a non-transmitting period (used in Hi-power X-Band wave-guide RG51/U). The operational band is nominally  $\pm$  3% depending on specific application. Former type designation was ATR 321.

#### SYLVANIA ELECTRIC PRODUCTS INC.

ELECTRONICS DIVISION WOBURN, MASS.

Prepared and Released By The TECHNICAL PUBLICATIONS SECTION EMPORIUM, PENNSYLVANIA JULY 1956 PAGE 1 OF 2 SYLVANIA 5864 page 2



#### NOTES:

- 1. The tubulation shall fall within a circle of 3% inch max. diameter located from the centerlines of the flange.
- 2. Silver plate 100 M.S.I. or equivalent.
- 3. Applies at all edges of bottom face of end plate only.
- 4. Centerlines of window shall coincide with corresponding centerlines of body within .015 inch. This measurement shall be made in the plane of the window.