-PRODUCT INFORMATION -



Diode Diode

6DK3

FOR TV DAMPING DIODE APPLICATIONS

■ COLOR TV TYPE

■ LOW TUBE DROP

■ 6,500 VOLTS DC AND PEAK

■ 400 MILLIAMPERES DC

The 6DK3 is a heater—cathode type diode intended for service as the damping diode in the horizontal—deflection circuit of color television receivers. It utilizes a unique heater—cathode insulating system making possible a rating of 6,500 volts peak. The 6DK3 also features a top cap connection to the cathode, a T—9 bulb and a 9—pin glass button base with a 0.687—inch pin circle.

GENERAL

ELECTRICAL	
Cathode - Coated Unipotential	
Heater Characteristics and Ratings Heater Voltage, AC or DC★	Amperes pf
Heater to Cathode: (h to k)	


MECHANICAL

MAXIMUM RATINGS

TV DAMPER SERVICE*-DESIGN-MAXIMUM VALUES

Peak Inverse Plate Voltage 6,500 Plate Dissipation	Volts Watts
Steady-State Peak Plate Current	Milliamperes
DC Output Current	Milliamperes
Heater-Cathode Voltage	
Heater Positive with respect to Cathode	
DC Component	Volts
Total DC and Peak	Volts
Heater Negative with respect to Cathode	
DC Component	Volts
Total DC and Peak	
Bulb Temperature ⊕	°C

PHYSICAL DIMENSIONS



TERMINAL CONNECTIONS §

Pin 1 - Heater Insulation Coil

Pin 2 - Plate

Pin 3 - No Connection

Pin 4 - Heater

Pin 5 - Heater

Pin 6 - Internal Connection - Do Not Use

Pin 7 - Plate

Pin 8 - Internal Connection - Do Not Use

§ Pin 9 - No Connection

Cap - Cathode

BASING DIAGRAM



EIA 9SG



MAXIMUM RATINGS (Cont'd)

Design-Maximum ratings are limiting values of operating and environmental conditions applicable to a bogey electron tube of a specified type as defined by its published data and should not be exceeded under the worst probable conditions.

The tube manufacturer chooses these values to provide acceptable serviceability of the tube, making allowance for the effects of changes in operating conditions due to variations in the characteristics of the tube under consideration.

The equipment manufacturer should design so that initially and throughout life no design-maximum value for the intended service is exceeded with a bogey tube under the worst probable operating conditions with respect to supply-voltage variation, equipment component variation, equipment control adjustment, load variation, signal variation, environmental conditions, and variations in the characteristics of all other electron devices in the equipment.


Tube Voltage Drop	AVERAGE CHARACTERISTICS		
lb = 400 Milliamperes		16	Volts
lb = 800 Milliamperes		25	Volts
	NOTES		

- * The equipment designer should design the equipment so that heater voltage is centered at the specified bogey value, with heater supply variations restricted to maintain heater voltage within the specified tolerance.
- Heater current of a bogey at Ef = 6.3 volts.
- Without external shield.
- For operation in a 525-line, 30-frame television system as described in "Standards of Good Engineering Practice Con-

The tubes and arrangements disclosed herein may be covered by patents of General Electric Company or others. Neither the disclosure of any information herein nor the sale of tubes by General Electric Company conveys any license under patent claims covering combinations of tubes with other devices or elements. In the absence of an

- cerning Television Broadcast Stations," Federal Communications Commission. The duty cycle of the voltage pulse must not exceed 15 percent of one scanning cycle.
- Measured with an infrared thermometer, Ircon Model 700 BC or equivalent
- § May be used as a tie point for components at or near heater potential.

express written agreement to the contrary, General Electric Company assumes no liability for patent infringement arising out of any use of the tubes with other devices or elements by any purchaser of tubes or others.





TUBE PRODUCTS DEPARTMENT OWENSBORO, KENTUCKY 42301