



# engineering data service 8XP4

### CHARACTERISTICS

GENERAL DATA	
Focusing Method Self Focusing (Electrostatic)	
Deflecting Method	
Deflection Angles (approx.)	
Vertical	
Horizontal	
Diagonal	tees
Phosphor	
Fluorescence White	
Persistence Short to Medium	
Faceplate Gray Filter Glass	
Light Transmittance (approx.) 80 Perc	ent

### ELECTRICAL DATA

Heater Voltage	
Heater Current (approx.)	0.6 Ampere
Direct Interelectrode Capacitances (approx.)	
Cathode to All Other Electrodes	5 µµf
Grid No. 1 to All Other Electrodes	6 µµf

### MECHANICAL DATA

Minimum Useful Screen Dimensions		7-3/1	6 x 5¾	Inches
Bulb Contact (Recessed Small Cavity Cap)			J1-21	
Base (Small Shell Duodecal 5-Pin)			<b>Š5-</b> 57	
Basing		· •	12S	

### RATINGS

### MAXIMUM RATINGS (Absolute Maximum Values)

Anode Voltage	22,000 Volts dc
Grid No. 2 (and Grid No. 4) Voltage	. 550 Volts dc
Grid No. 1 Voltage	
Negative Bias Value	. 155 Volts dc
Negative Peak Value	
Positive Bias Value	. 0 Volts dc
Positive Peak Value	
Peak Heater-Cathode Voltage	
Heater Negative with Respect to Cathode	
During Warm-up Period not to Exceed	
15 Seconds	. 450 Volts
After Equipment Warm-up Period	. 200 Volts
Heater Positive with Respect to Cathode	. 200 Volts

### TYPICAL OPERATING CONDITIONS

Anode Voltage			• •	16,000 Volts dc
Grid No. 2 (and Grid No. 4) Voltage .				300 Volts dc
Grid No. 1 Voltage Required for Cutoff <sup>1</sup>	•	•	-28 to	o –72 Volts dc

### **CIRCUIT VALUES**

Grig No. I Circuit Resistance	Grid No.	Io. 1 Circuit Resistance											1.5 Megohms Max
-------------------------------	----------	--------------------------	--	--	--	--	--	--	--	--	--	--	-----------------

### NOTE:

1. Visual extinction of raster.

### QUICK REFERENCE DATA

Receiver Check Tube 8" Rectangular, All Glass Self Focusing (Electrostatic) No Ion Trap Magnetic Deflection Gray Filter Glass





### SYLVANIA ELECTRIC PRODUCTS INC.

#### TELEVISION PICTURE TUBE DIVISION

### SENECA FALLS, NEW YORK

Prepared and Released By The TECHNICAL PUBLICATIONS SECTION EMPORIUM, PENNSYLVANIA APRIL 1956

### SYLVANIA

## BXP4 PAGE 2



### **DIAGRAM NOTES:**

- 1. Reference line is determined by the plane C-C' of the reference line gauge (JETEC No. 116) when the gauge is resting on the glass cone.
- 2. Anode contact aligns with vacant pin position No.  $6 \pm 30$  degrees.

### WARNING:

X-ray radiation shielding may be necessary to protect against possible danger of personal injury from prolonged exposure at close range if this tube is operated at higher than the manufacturer's Maximum Rated Anode Voltage or 16,000 volts, whichever is less.