

Silicon PNP Power Transistors

2N6132 2N6133 2N6134

DESCRIPTION

- With TO-220 package
- High power dissipation
- Complement to NPN type :
 2N6129 2N6130 2N6131

APPLICATIONS

- Power amplifier and medium speed switching applications

PINNING

PIN	DESCRIPTION
1	Emitter
2	Collector;connected to mounting base
3	Base




Fig.1 simplified outline (TO-220) and symbol

Absolute maximum ratings(Ta=25°C)

SYMBOL	PARAMETER	CONDITIONS	VALUE	UNIT
V _{CBO}	Collector-base voltage	2N6132	-40	V
		2N6133	-60	
		2N6134	-80	
V _{CEO}	Collector-emitter voltage	2N6132	-40	V
		2N6133	-60	
		2N6134	-80	
V _{EBO}	Emitter-base voltage	Open collector	-5	V
I _C	Collector current		-7	A
I _B	Base current		-3	A
P _T	Total power dissipation	T _C =25	50	W
T _J	Junction temperature		150	
T _{stg}	Storage temperature		-65~150	

THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	MAX	UNIT
R _{th-jc}	Thermal resistance from junction to case	2.5	°W

NJ Semi-Conductors reserves the right to change test conditions, parameters limits and package dimensions without notice information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.



CHARACTERISTICS

T_j=25 unless otherwise specified

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP.	MAX	UNIT
V _{CE0(SUS)}	Collector-emitter sustaining voltage	2N6132	-40			V
		2N6133	-60			
		2N6134	-80			
V _{CEsat}	Collector-emitter saturation voltage	2N6132			-1.4	V
		2N6133				
		2N6134			-1.8	
V _{BE}	Base-emitter on voltage	I _C =-2.5A ; V _{CE} =-4V			-1.4	V
I _{CEV}	Collector cut-off current	2N6132			-0.5 -3.0	mA
		2N6133			-0.5 -3.0	
		2N6134			-0.5 -3.0	mA
I _{EBO}	Emitter cut-off current	V _{EB} =-5V ; I _C =0			-1.0	mA
h _{FE}	DC current gain	I _C =-2.5A ; V _{CE} =-4V	20		100	
f _r	Transition frequency	I _C =-0.2A ; V _{CE} =-4V	2.5			MHz

