FAIRCHILD January 2009 SEMICONDUCTOR OFE FQD20N06 / FQU20N06 **60V N-Channel MOSFET General Description** Features 16.8A, 60V, R_{DS(on)} = 0.063Ω @ V_{GS} = 10V Low gate charge (typical 11.5 nC) These N-Channel enhancement mode power field effect transistors are produced using Fairchild's proprietary, planar stripe, DMOS technology. • Low Crss (typical 25 pF) This advanced technology has been especially tailored to Fast switching minimize on-state resistance, provide superior switching • 100% avalanche tested performance, and withstand high energy pulse in the Improved dv/dt capability avalanche and commutation mode. These devices are well 150°C maximum junction temperature rating suited for low voltage applications such as automotive, DC/ RoHS Compliant DC converters, and high efficiency switching for power management in portable and battery operated products. D



I-PAK FQU Series



FQD20N06 / FQU20N06

Absolute Maximum Ratings T_c = 25°C unless otherwise noted

Symbol	Parameter		FQD20N06 / FQU20N06	Units
V _{DSS}	Drain-Source Voltage		60	V
I _D	Drain Current - Continuous (T _C = 25°	°C)	16.8	А
	- Continuous (T _C = 10	O°C)	10.6	А
I _{DM}	Drain Current - Pulsed	(Note 1)	67.2	А
V _{GSS}	Gate-Source Voltage		± 25	V
E _{AS}	Single Pulsed Avalanche Energy (Note 2)		155	mJ
I _{AR}	Avalanche Current	(Note 1)	16.8	А
E _{AR}	Repetitive Avalanche Energy	(Note 1)	3.8	mJ
dv/dt	Peak Diode Recovery dv/dt	(Note 3)	7.0	V/ns
P _D	Power Dissipation ($T_A = 25^{\circ}C$) *		2.5	W
	Power Dissipation ($T_C = 25^{\circ}C$)		38	W
	- Derate above 25°C		0.30	W/°C
T _J , T _{STG}	Operating and Storage Temperature Range		-55 to +150	°C
Τ _L	Maximum lead temperature for soldering purposes, 1/8" from case for 5 seconds		300	°C

Thermal Characteristics

Symbol	Parameter	Тур	Max	Units
$R_{\theta JC}$	Thermal Resistance, Junction-to-Case		3.28	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction-to-Ambient *		50	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction-to-Ambient		110	°C/W

©2009 Fairchild Semiconductor Corporation

	Parameter	Test Conditions	Min	Тур	Max	Units
Off Cha	aracteristics					
BV _{DSS}	Drain-Source Breakdown Voltage	V _{GS} = 0 V, I _D = 250 μA	60			V
ΔBV _{DSS} / ΔT _J	Breakdown Voltage Temperature Coefficient	$I_D = 250 \ \mu$ A, Referenced to 25°C		0.07		V/°C
IDSS	Zara Cata Valtaga Drain Current	$V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}$			1	μA
	Zero Gate Voltage Drain Current	V _{DS} = 48 V, T _C = 125°C			10	μA
I _{GSSF}	Gate-Body Leakage Current, Forward	$V_{GS} = 25 V, V_{DS} = 0 V$			100	nA
I _{GSSR}	Gate-Body Leakage Current, Reverse	$V_{GS} = -25 \text{ V}, \text{ V}_{DS} = 0 \text{ V}$			-100	nA
On Cha	aracteristics					
V _{GS(th)}	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu A$	2.0		4.0	V
R _{DS(on)}	Static Drain-Source On-Resistance	$V_{GS} = 10 V, I_{D} = 8.4 A$		0.050	0.063	Ω
9 _{FS}	Forward Transconductance	$V_{DS} = 25 \text{ V}, I_D = 8.4 \text{ A}$ (Note 4)		10		S
Dynam	ic Characteristics					
C _{iss}	Input Capacitance	V _{DS} = 25 V, V _{GS} = 0 V,		450	590	pF
C _{oss}	Output Capacitance	f = 1.0 MHz		170	220	pF
Crss	Reverse Transfer Capacitance			25	35	pF
d(on) r	Turn-On Delay Time Turn-On Rise Time	$V_{DD} = 30$ V, $I_D = 10$ A, R _G = 25 Ω		5 45	20 100	ns ns
t _r		$R_{G} = 25 \Omega$				
	Turn-Off Delay Time	(Note 4, 5)		20 25	50	ns
	Turn Off Fall Time			20	60	ns
f	Turn-Off Fall Time				45	
f Qg	Total Gate Charge	V _{DS} = 48 V, I _D = 20 A,		11.5	15	nC
f Q _g Q _{gs}	Total Gate Charge Gate-Source Charge	V _{DS} = 48 V, I _D = 20 A, V _{GS} = 10 V		11.5 3		nC nC
t _{d(off)} t _f Q _g Q _{gs} Q _{gd}	Total Gate Charge Gate-Source Charge Gate-Drain Charge	V_{DS} = 48 V, I _D = 20 A, V _{GS} = 10 V (Note 4, 5)		11.5		nC
t _f Q _g Q _{gs} Q _{gd} Drain-S	Total Gate Charge Gate-Source Charge Gate-Drain Charge	$V_{DS} = 48 \text{ V}, I_D = 20 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5)		11.5 3 4.5		nC nC nC
կ Q _g Q _{gs} Q _{gd} Drain-S	Total Gate Charge Gate-Source Charge Gate-Drain Charge Gource Diode Characteristics an Maximum Continuous Drain-Source Dio	$V_{DS} = 48 \text{ V}, I_D = 20 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5) Ad Maximum Ratings de Forward Current		11.5 3 4.5	 16.8	nC nC nC
t _f Q _g Q _{gs} Q _{gd} Drain-S Is	Total Gate Charge Gate-Source Charge Gate-Drain Charge Source Diode Characteristics ar Maximum Continuous Drain-Source Diode F Maximum Pulsed Drain-Source Diode F	$V_{DS} = 48 \text{ V}, I_D = 20 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5) nd Maximum Ratings de Forward Current Forward Current		11.5 3 4.5	 16.8 67.2	nC nC nC A A
t _f Q _g Q _{gs} Q _{gd} Drain-S Is S V _{SD}	Total Gate Charge Gate-Source Charge Gate-Drain Charge Source Diode Characteristics an Maximum Continuous Drain-Source Diode Maximum Pulsed Drain-Source Diode F Drain-Source Diode Forward Voltage	$V_{DS} = 48 \text{ V}, I_D = 20 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5) nd Maximum Ratings de Forward Current Forward Current $V_{GS} = 0 \text{ V}, I_S = 16.8 \text{ A}$	 	11.5 3 4.5 	 16.8 67.2 1.5	nC nC nC A A V
t _f Q _g Q _{gs} Q _{gd} Drain-S	Total Gate Charge Gate-Source Charge Gate-Drain Charge Source Diode Characteristics ar Maximum Continuous Drain-Source Diode F Maximum Pulsed Drain-Source Diode F	$V_{DS} = 48 \text{ V}, I_D = 20 \text{ A},$ $V_{GS} = 10 \text{ V}$ (Note 4, 5) nd Maximum Ratings de Forward Current Forward Current		11.5 3 4.5	 16.8 67.2	nC nC nC A A















SEMICONDUCTOR

TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

	Build it Now™ CorePLUS™ CorePOWER™ <i>CROSSVOLT™</i> CTL™ Current Transfer Logic™ EcoSPARK® EfficentMax™ EZSWITCH™ * Farchild® Fairchild® Fairchild® Fairchild Semiconductor® FACT® FAST® FAST® FAST® FastvCore™ FlashWriter® * FPST™	FRFET [®] Global Power Resource SM Green FPS™ e-Series™ GTO™ IntelliMAX™ ISOPLANAR™ MegaBuck™ MICROCOUPLER™ MicroFET™ MicroPak™ MillerDrive™ Motion-SPM™ OPTOLOGIC® OPTOPLANAR® ® PDP SPM™ Power-SPM™ PowerTrench® PowerYSTM	Programmable Active Droop [™] QFET [®] QS [™] Quiet Series [™] RapidConfigure [™] $\widetilde{O}_{T^{N}}$ Saving our world, 1mW /W /kW at a time [™] SmartMax [™] SMART START [™] SMART START [™] SMART START [™] SUPF [®] STEALTH [™] SuperSOT [™] -3 SuperSOT [™] -6 SuperSOT [™] -8 SuperSOT [®] -8 SuperS	the franchise TinyBoost™ TinyBoost™ TinyLogic® TINYOPTO™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM™ TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM TinyPWM
P-PFS ™ PowerXS™		PowerTrench [®]	The Power Franchise [®]	

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

EARCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Farichild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufactures of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed application, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Farichild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handing and storage and provide access to Farichild's full range of up-to-date technical and product information. Fairchild and our Authorized to behind all warranties and will appropriately address and warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Farichild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.